



Calhoun: The NPS Institutional Archive DSpace Repository

Theses and Dissertations

1. Thesis and Dissertation Collection, all items

1967-05

Approximate self-consistent field calculations of molecular potential surfaces

Yun, Chang Sop

Monterey, California. U.S. Naval Postgraduate School

<http://hdl.handle.net/10945/11696>

Copyright is reserved by the copyright owner

Downloaded from NPS Archive: Calhoun



<http://www.nps.edu/library>

Calhoun is the Naval Postgraduate School's public access digital repository for research materials and institutional publications created by the NPS community.

Calhoun is named for Professor of Mathematics Guy K. Calhoun, NPS's first appointed -- and published -- scholarly author.

Dudley Knox Library / Naval Postgraduate School
411 Dyer Road / 1 University Circle
Monterey, California USA 93943

NPS ARCHIVE
1967
YUN, C.

APPROXIMATE SELF-CONSISTENT FIELD CALCULATIONS OF MOLECULAR POTENTIAL SURFACES

CHANG SOP YUN





APPROXIMATE
SELF-CONSISTENT FIELD CALCULATIONS
OF MOLECULAR POTENTIAL SURFACES

by

YUN, CHANG SOP
Lieutenant, Republic of Korea Navy
B.S., Naval Academy, 1961

Submitted in partial fulfillment of the
requirements for the degree of

MASTER OF SCIENCE IN CHEMISTRY

from the

NAVAL POSTGRADUATE SCHOOL
May 1967

NPS ARCHIVE

1967

YUN, C.

~~Drop you~~
c.1

ABSTRACT

The Approximate Self-Consistent Field Molecular Orbital Theory (ASCFT) with complete neglect of differential overlap (CNDO) has been applied to the calculation of electronic structure for several selected molecules in this text. The theory leads to calculated equilibrium geometry configurations and the barrier to internal rotation of ethane, inversion barrier of ammonia and the barrier for cis to trans conversion for difluorodiazine. These results are in reasonable agreement with experimental values in most cases. The stretching force constants are higher than experimental values by a factor of approximately two. The orbital energy levels for ammonia and for oxygen difluoride as a function of bond angles were in reasonable agreement with the full LCAO-SCF Calculations. A variation of parameters to find a new set of parameters was attempted with unsuccessful results.

The Extended Hückel Theory (EHT) can be applied to aliphatic hydrocarbons but its application to non-hydrocarbon molecules is quite limited.

LIBRARY

NAVAL POSTGRADUATE SCHOOL
MONTEREY, CALIF. 93940

TABLE OF CONTENTS

Section	Page
I Introduction	9
II Hückel molecular orbital theory	9
III Extended Hückel theory	15
IV Approximate self-consistent field Molecular orbital theory	17
1. SCF equation	19
2. Theory with complete neglect of differential overlap (CNDO)	21
3. Choice of Parameters of CNDO1 and CNDO2.	26
V Discussion of Results	28
1. Comparison of the equilibrium configurations and force constants.	29
2. Water molecule (H_2O).	30
3. Ammonia molecule (NH_3).	30
4. Ethane molecule (C_2H_6).	35
5. Methane and Methylfluoride (CH_4 and CH_3F).	38
6. Difluorodiazine (N_2F_2).	39
7. Oxygen difluoride.	43
8. Hydrogen Peroxide.	45
9. Homonuclear diatomic molecules	46
VI Conclusions	48
Bibliography	50
Appendix	
I Computer program for ASCFT.	53
II Computer output of H_2O (Sample).	94



LIST OF TABLES

1. Slater exponents for valence Shell S and P atomic orbitals.
2. Bonding parameters β_A^o (in e.v.).
3. "Average" ionization potentials I_μ (e.v.).
4. Difference between CND01 and CND02.
5. Matrix elements from atomic data. $U_{\mu\mu}$ (CND02).
6. Comparison of equilibrium geometry and force constants.
7. Calculation of R_{OH} and $\angle HOH$ for H_2O .
8. Comparison of the results of calculations for NH_3 .
9. Change in barrier for NH_3 w.r.t. minimizing parameters.
10. Comparison of Ethane between EHT. and ASCFT calculation.
11. Comparison of barrier for Ethane.
12. Comparison of r , θ , k_r and k_θ between CH_4 and CH_3F .
13. Results of experiments and calculations for N_2F_2 .
14. Equilibrium configuration between cis and trans for N_2F_2 molecule.
15. Comparison of barrier between $C_{2v}(C_2h)$ and $C_2(C_{2\infty})$ for N_2F_2 .
16. Equilibrium configurations and some partial derivatives for homonuclear diatomic molecules.

LIST OF ILLUSTRATIONS

1. Orbital Energy of NH_3 as a function of the pyramid height (ASCFT and full LCAOSCFT).
2. Orbital energy of NH_3 as a function of the Pyramid height (EHT).
3. Barrier for N_2F_2 as a function of $\angle \text{NNF}$
4. Orbital energy of F_2O as a function of $\angle \text{FOF}$. (ASCFT and full LCAOSCFT).
5. Structural parameters of H_2O_2 .

ACKNOWLEDGEMENT

The author wishes to express his appreciation to Dr. William M. Tolles for his continuous guidance and assistance in this project and also wishes to thank members of the computer facility of the United States Naval Postgraduate School for providing sufficient computation time.

I. INTRODUCTION

There are many levels of sophistication for the calculation of electronic structure using molecular orbital methods. The simplest approach is the Hückel Molecular Orbital Theory (HMO). This is one of the semiempirical methods which is used extensively in the quantum mechanical study of the mobile electrons of conjugated molecules. The HMO was extended by many people. One of the theories examined in this paper is the "Extended Hückel Theory (EHT)" which was developed by Roald Hoffmann (1). A higher level of sophistication is the self-consistent field (SCF) molecular orbital calculation. One of those methods which has recently been developed is based on a theory introduced by J. A. Pople: "Approximate Self-Consistent Field Molecular Orbital Theory (ASCFT)" (2), (3), (4). This ASCFT Calculation is predominantly used throughout this text.

We can say molecular orbital methods are "curve fitting". They are really based on semiempirical methods. The purposes of the calculation described herein are the prediction of potential surface by Pople's theory to examine and to try to improve the agreement of a calculated potential surface with an experimental potential surface.

The background describing each of these theories will be discussed in the next section.

II. Hückel Molecular Orbital Theory (HMO)

In this theory, the mobile electrons can be treated as occupying a set of delocalized molecular orbitals (by the Pauli Exclusion Principle, not more than two electrons in each molecular orbital). These molecular

orbitals are eigenfunctions of a one electron Hamiltonian. The orbitals are approximated by a linear combination of atomic orbitals (LCAO) centered on various atoms. The Slater type atomic orbitals (5) are generally used as approximations to the actual atomic orbitals for each atom. When this theory is applied to a wide range of molecules, it has the advantage of great simplicity but serious discrepancies result because of the neglect of interelectronic repulsions for the case of many electrons.

For the unsaturated molecules: The π - molecular orbitals are formed by a LCAO of the $2P_z$ atomic orbitals which, it is assumed, share the same nodal plane. In $N-\pi$ electron systems, the molecular orbitals are given by

$$\Psi_j = \sum_{\nu=1}^N C_{j\nu} \phi_\nu \quad (j=1, \dots, N) \quad (1.1)$$

where Ψ_j represents the j^{th} molecular orbital, ϕ_ν represents the atomic orbital in the ν^{th} atom and $C_{j\nu}$ represents the coefficients of the j^{th} molecular orbital and the ν^{th} atom (atomic orbital). It is noted that the subscript i, j, k, l etc. stand for the molecular orbitals and M, ν, σ, λ etc. stand for the atoms or atomic orbitals.

From a given electron Hamiltonian, Equation (1.1) must satisfy the equation

$$\mathcal{H}\Psi_j = E_j \Psi_j \quad (1.2)$$

Where E_j is the eigenvalue of the j^{th} state, Ψ_j is a column matrix, and \mathcal{H} is the Hamiltonian operator. This can be put in matrix form:

$$(\mathcal{H}) \begin{pmatrix} \Psi_1 \\ \vdots \\ \Psi_N \end{pmatrix} = \begin{pmatrix} E_1 & 0 & \cdots & 0 \\ 0 & E_2 & \ddots & 0 \\ \vdots & \ddots & \ddots & \vdots \\ 0 & \cdots & -0 & E_N \end{pmatrix} \begin{pmatrix} \Psi_1 \\ \vdots \\ \Psi_N \end{pmatrix} \quad (1.2)$$

We multiply equation (1.2) by Ψ_i^* and integrate over all space, $d\tau$, then we obtain

$$\int \Psi_i^* \mathcal{H} \Psi_j d\tau = \int \Psi_i^* E_j \Psi_j d\tau \quad (1.3)$$

Substituting equation (1.1) into (1.3)

$$\sum_{\mu, \nu} C_{i\mu}^* C_{j\nu} \int \phi_\mu^* \mathcal{H} \phi_\nu d\tau = \sum_{\mu, \nu} C_{i\mu}^* C_{j\nu} E_j \int \phi_\mu^* \phi_\nu d\tau \quad (1.4)$$

Defining

$$H_{\mu\nu} = \int \phi_\mu^* \mathcal{H} \phi_\nu d\tau \quad (1.5)$$

and

$$S_{\mu\nu} = \int \phi_\mu^* \phi_\nu d\tau \quad (1.6)$$

We may write equation (1.4)

$$\sum_{\mu, \nu} C_{i\mu} C_{j\nu} H_{\mu\nu} = E_j \sum_{\mu, \nu} C_{i\mu} C_{j\nu} S_{\mu\nu} \quad (1.7)$$

Taking the derivative of equation (1.7) with respect to $C_{k\lambda}$ to minimize the energy ($\partial E_j / \partial C_{k\lambda} = 0$), we obtain

$$\sum_{\mu} C_{k\mu} H_{\mu\lambda} + \sum_{\nu} C_{k\nu} H_{\lambda\nu} = E_k \left(\sum_{\mu} C_{k\mu} S_{\mu\lambda} + \sum_{\nu} C_{k\nu} S_{\lambda\nu} \right) \quad (1.8)$$

It may be shown that

$$S_{\mu\nu} = S_{\nu\mu} \quad (1.9)$$

$$H_{\mu\nu} = H_{\nu\mu} \quad (1.10)$$

Therefore we obtain the equation

$$\sum_{\mu} C_{k\mu} H_{\mu\lambda} = E_k \sum_{\mu} C_{k\mu} S_{\mu\lambda} \quad (1.11)$$

or

$$\sum_{\mu} C_{k\mu} (H_{\mu\lambda} - E_k S_{\mu\lambda}) = 0 \quad (1.12)$$

This equation (1.12) is the well-known secular equation and gives rise to the secular determinant:

$$| H_{\mu\lambda} - E_k S_{\mu\lambda} | = 0 \quad (1.13)$$

Equation (1.13) is the non-trivial solution of (1.12).

Now we discuss the Hermitian Property of the Matrices ($H_{\mu\lambda}$) and ($S_{\mu\lambda}$). A matrix H is said to be Hermitian if it is equal to the conjugate of its transpose, i.e.,

$$\overline{H'} = H$$

Where $H = (H_{\mu\lambda})$ and $\overline{H'} = (\overline{H}_{\lambda\mu})$ (1.14)
 $(\mu, \lambda = 1, 2, \dots, N)$

By definition, a real Hermitian matrix is symmetric, but an imaginary symmetric matrix is not necessarily an Hermitian matrix. It is noted that the eigenvalues of an Hermitian matrix are all real.

Next we discuss some transformation properties. In general, the atomic orbital ϕ_λ does not form a complete orthonormal set. This basis, ϕ_λ , can be transformed into an orthonormal basis by using a unitary transformation matrix such that

$$\phi_\lambda^{\text{new}} = \sum_{\sigma} T_{\sigma\lambda} \phi_\lambda^{\text{old}} \quad (1.15)$$

where $\phi_\lambda^{\text{new}}$ is the new orthonormal basis formed by transforming the old basis $\phi_\lambda^{\text{old}}$ in N dimensional space and $T_{\sigma\lambda}$ is the transformation matrix element. The old H can also be transformed into a new basis such that

$$H_{\mu\nu}^{\text{new}} = \sum_{\sigma, \lambda} T_{\mu\sigma}^* T_{\nu\lambda} \int \phi_\sigma^* \phi_\lambda d\tau \quad (1.16)$$

It may be recalled that the old basis is $H_{\sigma\lambda}^{\text{old}} = \int \phi_\sigma^* \phi_\lambda d\tau$.

Therefore equation (1.16) can be rewritten

$$H_{\mu\nu}^{\text{new}} = \sum_{\sigma, \lambda} T_{\mu\sigma}^* H_{\sigma\lambda}^{\text{old}} T_{\nu\lambda} \quad (1.16)'$$

or

$$H_{\mu\nu}^{\text{new}} = \sum_{\sigma, \lambda} T_{\mu\sigma}^* H_{\sigma\lambda}^{\text{old}} T_{\lambda\nu}' \quad (1.17)$$

It is noted that if the transformations were made:

$$\phi_{\nu}^{\text{new}} = \sum_{\lambda} \phi_{\lambda} T_{\lambda\nu} \quad (1.18)$$

then the equation (1.17) becomes

$$H_{\mu\nu}^{\text{new}} = \sum_{\sigma, \lambda} T_{\mu\sigma}^{*\prime} H_{\sigma\lambda}^{\text{old}} T_{\lambda\nu} \quad (1.19)$$

Equations (1.17) and (1.19) can be written by matrix notation such that

$$H^{\text{new}} = T^* H^{\text{old}} T' \quad (1.17)'$$

and

$$H^{\text{new}} = T^{*\prime} H^{\text{old}} T \quad (1.19)'$$

From equation (1.19)', if T is a unitary matrix ($T^{-1} = T^*$) then we have

$$H^{\text{new}} = T^{-1} H^{\text{old}} T \quad (1.20)$$

This equation (1.20) is frequently used and usually T is real and H^{old} is a symmetric matrix.

Referring to the secular equation (1.12), we define $\lambda_{kk} = E_k$, then

$$\sum_{\mu} (H_{\lambda\mu} C_{\mu k} - S_{\lambda\mu} C_{\mu k} \lambda_{kk}) = 0 \quad (1.21)$$

This can be expressed in matrix notation in the following manner

$$HC - SC\lambda = 0 \quad (1.21)'$$

where

$$H = (H_{\lambda\mu}) \quad \lambda = (\lambda_{kk})$$

$$C = (C_{\mu k})$$

$$S = (S_{\lambda\mu}) \quad (\lambda, \mu, k = 1, \dots, N)$$

Therefore, we obtain

$$\lambda = (\lambda_{kk}) = C^{-1}(S^{-1}H)C \quad (1.22)$$

It is generally true that the matrix $(S^{-1}H)$ may not be symmetric. In equation (1.22), the eigenvalue cannot be obtained by methods usually employed to diagonalize Hermitian matrices. One way to solve this problem is to transform the matrix S to an orthonormal basis, then diagonalize the H matrix. The procedures are described as follows: Using the transformation matrix Q such that $\Psi = Q\phi$, we transform the matrix S to the identity matrix I

$$S^{\text{new}} = I = QS^{\text{old}}Q' \quad (1.23)$$

or

$$S^{\text{old}} = (Q'Q)^{-1} \quad (1.24)$$

Also we diagonalize the matrix S by a unitary transformation matrix T such that

$$\lambda = TS^{\text{old}}T' \quad (1.25)$$

or

$$\begin{aligned} S^{\text{old}} &= (T'\lambda^{-1}T)^{-1} \\ &= [(T\lambda^{-\frac{1}{2}}T)'(T\lambda^{-\frac{1}{2}}T)]^{-1} \end{aligned} \quad (1.26)$$

Equating equation (1.24) and (1.26), we obtain

$$Q = T\lambda^{-\frac{1}{2}}T \quad (1.27)$$

Then we transform the old basis H to the new basis by the transformation matrix Q such that

$$\begin{aligned} H^{\text{new}} &= QH^{\text{old}}Q' \\ &= (T\lambda^{-\frac{1}{2}}T)(H^{\text{old}})(T\lambda^{-\frac{1}{2}}T)' \end{aligned} \quad (1.28)$$

Finally we can diagonalize H^{new} by the matrix U . Then we obtain the eigenvalues

$$\begin{aligned} E &= UH^{\text{new}}U' \\ &= (UT\lambda^{-\frac{1}{2}}T)(H^{\text{old}})(UT\lambda^{-\frac{1}{2}}T)' \end{aligned} \quad (1.29)$$

where U is the matrix which diagonalizes the H^{new} and T is the unitary matrix which diagonalizes S . Also the correct eigenfunctions are

$$\Psi = UT'\lambda^{-\frac{1}{2}}T\phi \quad (1.30)$$

The general operations for the application of HMO theory to specific problems are

- (a) Setting up the Secular determinant
- (b) Expanding the Secular determinant
- (c) Finding the eigenvalues
- (d) Determining the M.O.'s by finding the eigenvectors.

III. Extended Hückel Theory (EHT)

Hückel calculations originally were applied exclusively for the Planar conjugated and aromatic systems of π electrons with the neglect of overlap for non-adjacent atoms. In the extended Hückel theory (EHT), Roald Hoffmann (1) expanded the basis set to consist of 2s and 2P orbitals for Carbon atoms and 1s orbitals for Hydrogen, with the inclusion of all overlap integrals. The EHT can calculate molecular orbitals for the aliphatic and aromatic compounds which gives good results for most hydrocarbons because of the reasonable set of parameters chosen for the calculations. The parameters are nicely adjusted to the self-consistent value for the hydrocarbons but when the EHT is applied to non-hydrocarbons, it is not as successful, and even predicts a lack of minima in many bond stretching motions.

III-A. Method of Calculation

For the calculation of the molecule C_nH_m , we use a basis set

consisting of m-Hydrogen Slater orbitals, n-2s and 3n-2P orbitals. The Slater exponents were selected to be 1.0 for Hydrogen and 1.625 for Carbon throughout the calculations. It is noted that 1.20 was selected for Hydrogen in the calculation of the ethane molecule. Those values are listed in Table 1. The order of the matrix is $4n + m$ which gives the number of energy levels of the system and the eigenvalue E's for off diagonal matrix elements are retained in the Secular Equation.

TABLE 1

Slater exponents for valence Shell S and P atomic orbitals.

H	1.0*	C ⁻	1.45	O ⁻	2.10
Li	0.65	C	1.625	O	2.275
Be	0.975	C ⁺	1.80	O ⁺	2.45
B ⁻	1.125	N	1.95	F	2.60
B	1.30	N ⁺	2.125		

* Present calculations we carried out using 1.2 for Hydrogen.

The diagonal elements $H_{\mu\mu}$ are chosen to be valence state ionization potentials; the particular values used are essentially those of Skinner and Pritchard (6). For example, the SP³ valence state ionization potentials for Carbon and 1s Hydrogen atoms have the following values:

$$H_{\mu\mu}(C_{2p}) = -11.4 \text{ e.v.}$$

$$H_{\mu\mu}(C_{2s}) = -21.4 \text{ e.v.} \quad (2.1)$$

$$H_{\mu\mu}(H_s) = -13.6 \text{ e.v.}$$

The choice of the off-diagonal term $H_{\mu\nu}$ is approximated as

$$H_{\mu z} = 0.5 K (H_{\mu\mu} + H_{zz}) (S_{\mu z}) \quad (2.2)$$

The approximation (2.2) was first discussed by Mulliken (7) and used in the M.O. Calculations by Wolfsberg and Helmholtz (8).

The value of K in equation (2.2) was chosen to be 1.75. These calculations give fairly good results for hydrocarbons.

IV. Approximate Self-Consistent Field Molecular Orbital Theory (ASCFT)

Approximate methods for obtaining self-consistent field molecular orbitals have recently been developed by J. A. Pople (2), (3), (4).

Slater type orbitals (5) are used as basis functions. Overlap integrals between two different atoms were calculated using the formula given by Mulliken, Rieke, Orloff and Orloff (9). It is assumed that the Slater type atomic orbitals are real atomic orbitals, and that the M.O.'s for the ground state are obtained by Linear Combinations of Slater type atomic orbitals. If the Coefficients in the LCAO Molecular orbitals are chosen to minimize the total energy, one obtains LCAO - SCF orbitals. The best LCAO approximation to SCF functions were first given by Roothaan (10). It is noted that the EHT treated all the electrons independently. EHT wave functions are used as a starting point for the self-consistent field interations in this ASCFT.

The SCF methods were developed using two approximations based on the neglect of the differential overlap between all valence atomic orbitals. One of these involves complete neglect of differential overlap (CNDO) in all basis sets connected by the transformations as mentioned in Section I, that is: the off-diagonal elements of overlap matrix in the Hamiltonian matrix are to be neglected. The other involves the

neglect of the products of $\phi_{\mu(1)} \phi_{\nu(1)}$ of any two atomic orbitals ϕ_{μ} and ϕ_{ν} in all electron-repulsion integrals. This complete neglect of differential overlap of all basis sets will result in non-orthonormal basis sets.

The CNDO method in ASCFT should be regarded as an approximation to a full LCAO - SCF calculation which uses a minimal basis containing only inner-shell and valence-shell atomic orbitals. The Slater exponents used in these calculations are listed in Table 1 (for Hydrogen, 1.2 is used). The values for β^o and ionization potentials in 2s and 2p atomic orbitals from Lithium to Fluorine were set semiempirically. Those values used in these calculations are tabulated in Table 2 and Table 3 respectively.

Atom	H	Li	Be	B	C	N	O	F
	9	9	13	17	21	25	31	39

Atom	H	Li	Be	B	C	N	O	F
1s	13.06	--	--	--	--	--	--	--
2s	--	5.39	9.32	14.05	19.44	25.58	32.38	40.20
2P	--	3.54	5.96	8.30	10.67	13.19	15.85	18.66

The CNDO method of ASCFT can be used for closed ground shell structures and doublets, but a triplet structure is not available with the computer program used (for example O₂, B₂ and C₂). The computer program is presented in Appendix 1.

IV-1. Self-Consistent Field (SCF) Equation

The initial discussion covers Roothann's LCAO - SCF method (10) as a basis for calculating the MO's of a molecule, paying particular attention to transformation properties. The 1s Hydrogen and valence shell electrons for Li to F are assigned to LCAO molecular orbitals. Minimization of total energy by a variation principle with SCF orbitals leads to a series of simultaneous non-Linear equations, the so called Hartree Fock equations (11), which are applied to LCAO molecular orbitals with a closed shell configuration. These equations were shown by Roothaan to reduce to the form (10)

$$\sum_{\lambda} F_{\mu\nu} C_{\lambda i} = \sum_{\lambda} S_{\mu\nu} C_{\lambda i} \epsilon_i \quad (4.1)$$

where (using atomic units)

$$F_{\mu\nu} = H_{\mu\nu} + G_{\mu\nu} \quad (4.2)$$

$$H_{\mu\nu} = \int \phi_{\mu}^* \left(-\frac{1}{2} \nabla^2 - \sum_A V_A(r) \right) \phi_{\nu} d\tau \quad (4.3)$$

$$G_{\mu\nu} = \sum_{\lambda, \sigma} P_{\lambda\sigma} \left[(\mu\nu|\lambda\sigma) - \frac{1}{2} (\mu\sigma|\nu\lambda) \right] \quad (4.4)$$

$$(\mu\nu|\lambda\sigma) = \iint \phi_{\mu}^{*(1)} \phi_{\nu}^{(1)} \frac{1}{r_{12}} \phi_{\lambda}^{*(2)} \phi_{\sigma}^{(2)} d\tau_1 d\tau_2 \quad (4.5)$$

$$S_{\mu\nu} = \int \phi_\mu^* \phi_\nu d\tau \quad (4.6)$$

$$P_{\lambda\sigma} = 2 \sum_i^{occ} C_{i\lambda}^* C_{i\sigma} \quad (4.7)$$

Where E_i is the orbital energy for the i^{th} M.O. $H_{\mu\nu}$ is the matrix element of the one electron Hamiltonian including the kinetic energy and the Potential energy in the electrostatic field of the core, this being written as a sum of potentials $V_A(r)$ for various atoms A in the molecule. $G_{\mu\nu}$ is the matrix element of the potential due to valence electrons and depends on the M.O.'s via the population matrix $P_{\lambda\sigma}$.

The total energy of the molecule is obtained by adding the repulsion energy between isolated cores and the separated valence electrons. The repulsion term can be approximated by a point charge model

$$E_{\text{total}} = E_{\text{electronic}} + \sum_{A \in B} Z_A Z_B / R_{AB} \quad (4.8)$$

where Z_A is the core charge of atom A. The electronic energy is given by

$$E_{\text{operator}} = 2 \sum_i H_i + \sum_{i,j} (2J_{ij} - K_{ij}) \quad (4.9)$$

$$E_{\text{electronic}} = 2 \sum_{M.O., i} C_{ui} G_{ui} H_{\mu\nu} + \sum_{M.O., i} C_{ui} G_{ui} G_{\mu\nu}$$

$$= \sum_{M.O.} P_{\mu\nu} H_{\mu\nu} + \frac{1}{2} \sum_{M.O.} P_{\mu\nu} G_{\mu\nu}$$

$$E_{\text{elect.}} = \frac{1}{2} \sum_{\mu, \nu} P_{\mu\nu} [2H_{\mu\nu} + G_{\mu\nu}]$$

$$= \frac{1}{2} \sum_{\mu, \nu} P_{\mu\nu} [H_{\mu\nu} + F_{\mu\nu}] \quad (4.10)$$

IV-2. Theory with Complete Neglect of Differential Overlap (CNDO)

First consider the simplest version of the theory which involves the complete neglect of differential overlap between atomic orbitals on the same atom. The approximations are given below.

Approximation A

The atomic orbitals ϕ_μ are treated as if they form an orthonormal set such that $S_{\mu\nu} = \delta_{\mu\nu}$ and then the $C_{i\mu}$ forms an orthonormal matrix. The condition for orthonormality becomes:

$$\sum_{\mu} C_{i\mu} C_{j\mu} = \delta_{ij} \quad (4.11)$$

With this approximation, the diagonal matrix elements $P_{\mu\mu}$ (electron density) correspond to the electron populations of the atomic orbitals ϕ_μ and

$$\sum_{\mu} P_{\mu\mu} = 2N \quad (4.12)$$

where $2N$ is the number of valence electrons.

Approximation B.

Equations (4.4) are neglected because of the orthonormality of atomic orbitals. This means $(\mu\sigma | \lambda\sigma)$ is zero unless $\mu = \lambda$ and $\sigma = \sigma$. The non-zero values will be written $T_{\lambda\mu}$ such that

$$\gamma_{\lambda\mu} = (\lambda\lambda | \mu\mu)$$

(4.13)

Approximation C

The electron-interaction integrals $\gamma_{\lambda\mu}$ are assumed to depend only on the atoms to which the orbitals ϕ_λ and ϕ_μ belong and not on the actual type of the orbitals. This means that there remains only a set of atomic electron-interaction integrals γ_{AB} measuring an average repulsion between an electron in valence atomic orbital on atom A and another in a valence orbital on atom B. The set of atomic orbitals on one particular atom A is replaced by an alternative set t_m ,

$$t_m = \sum_\mu O_{m\mu} \phi_\mu \quad (4.14)$$

A general electron-repulsion integral in this new basis set is given by

$$(t_m t_n | \phi_\lambda \phi_\lambda) = \sum_\mu O_{m\mu} O_{n\mu} (\phi_\mu \phi_\mu | \phi_\lambda \phi_\lambda) \quad (4.15)$$

Now we apply approximation C, then equation (4.15) becomes

$$(t_m t_n | \phi_\lambda \phi_\lambda) = \gamma_{AB} \delta_{mn} \quad (4.16)$$

It is noted that equation (4.16) is invariant under the orthogonal transformation matrix \mathbf{O} which gives the new basis t .

Using approximation A, and B, the matrix elements $F_{\lambda\mu}$ become

$$\begin{aligned} F_{\lambda\mu} &= H_{\lambda\mu} + G_{\lambda\mu} \\ &= H_{\lambda\mu} + \sum_{\sigma} P_{\lambda\sigma} [(\mu\mu | \lambda\sigma) - \frac{1}{2}(\mu\sigma | \mu\lambda)] \\ &= H_{\lambda\mu} - \frac{1}{2} P_{\lambda\mu} \gamma_{\lambda\mu} + \sum_{\sigma(\neq\mu)} P_{\sigma\sigma} \gamma_{\mu\sigma} \end{aligned} \quad (4.17)$$

$$F_{\mu\nu} = H_{\mu\nu} - \frac{1}{2} P_{\mu\nu} \gamma_{\mu\nu} \quad (4.18)$$

Equation (4.17) and (4.18) can be rewritten by approximation C

$$F_{\mu\mu} = H_{\mu\mu} - \frac{1}{2} P_{\mu\mu} \gamma_{AA} + P_{AA} \gamma_{AA} + \sum_{B \neq A} P_{BB} \gamma_{AB} \quad (4.19)$$

$$F_{\mu\nu} = H_{\mu\nu} - \frac{1}{2} P_{\mu\nu} \gamma_{AB} \quad (4.20)$$

where μ belongs to atom A and P_{BB} is the total valence electron density on atom B.

$$P_{BB} = \sum_z {}^B P_{zz} \quad (4.21)$$

Also the core matrix $H_{\mu\mu}$ can be separated as follows:

$$\begin{aligned} H_{\mu\mu} &= (\mu | -\frac{1}{2} \nabla^2 - V_A | \mu) - \sum_{B \neq A} (\mu | V_B | \mu) \\ &= U_{\mu\mu} - \sum_{B \neq A} (\mu | V_B | \mu) \end{aligned} \quad (4.22)$$

$$H_{\mu\nu} = U_{\mu\nu} - \sum_{B \neq A} (\mu | V_B | \nu) \quad (4.23)$$

where $U_{\mu\mu}$ is the diagonal element of ϕ_μ with respect to the one-electron Hamiltonian containing only the core of its own atom ($U_{\mu\mu}$ is an atomic quantity measuring the energy of the atomic orbital) and $U_{\mu\nu}$ is the one-electron matrix element using the local core Hamiltonian (μ and ν are on the

same atoms). It is noted that the cores consist of the nucleus and inner-shell electron.

Approximation D

The interaction terms of the distribution $\phi_\mu \phi_\nu$ on atom A and the nucleus of atom B, $(\mu | V_B | \nu)$ are equal to zero if $\mu \neq \nu$. The integrals $(\mu | V_B | \nu)$ are taken to be the same for all valence atomic orbitals on Atom A and there results

$$V_{AB} = (\mu | V_B | \mu) \quad (4.24)$$

It should be noted that the attraction term matrix element V_{AB} between nucleus B and the adjacent valence electron μ in the field of the nucleus A need not be symmetric. Therefore the equations (4.22) and (4.23) can be rewritten

$$H_{\mu\mu} = U_{\mu\mu} - \sum_{B(\neq A)} V_{AB} \quad (\mu \text{ on atom } A) \quad (4.25)$$

$$H_{\mu\nu} = 0 \quad (\mu \neq \nu; \begin{matrix} \text{both on the} \\ \text{same atom} \end{matrix}) \quad (4.26)$$

It is noted that $H_{\mu\nu} \neq 0$ if ϕ_μ and ϕ_ν are on different atoms which will be discussed in the next approximation.

Approximation E

If ϕ_μ and ϕ_ν are on different atoms, it is only necessary to consider the possible lowering of energy levels by being in the electrostatic field of two atoms simultaneously which is referred to as a "Resonance Integral" and is denoted by $\beta_{\mu\nu}$. $H_{\mu\nu}$ can be

approximated as

$$H_{\mu\nu} \approx \beta_{\mu\nu} = \beta_{AB}^o S_{\mu\nu} \quad (4.27)$$

where β_{AB}^o is a parameter depending only on the nature of the atoms A and B. Empirical values will be used for these parameters.

The $F_{\mu\nu}$ matrix elements now reduce to the form from equation (4.19) to (4.27)

$$F_{\mu\mu} = U_{\mu\mu} + \left(P_{AA} - \frac{1}{2} P_{\mu\mu} \right) \gamma_{AA} + \sum_{B(\neq A)} \left(P_{BB} \gamma_{AB} - V_{AB} \right) \quad (4.28)$$

$$F_{\mu\nu} = \beta_{AB}^o S_{\mu\nu} - \frac{1}{2} P_{\mu\nu} \gamma_{AB} \quad (\mu \neq \nu) \quad (4.29)$$

where ϕ_μ belongs to atom A and ϕ_ν belongs to atom B.

Using the same approximations, the total energy is given by one or two atom types from the equation (4.8)

$$E_{\text{total}} = \sum_A E_A + \sum_{A < B} E_{AB}$$

where

$$E_A = \sum_{\mu}^A P_{\mu\mu} U_{\mu\mu} + \frac{1}{2} \sum_{\mu}^A \sum_{\nu}^A \left(P_{\mu\mu} P_{\nu\nu} - \frac{1}{2} P_{\mu\nu}^2 \right) \gamma_{AA} \quad (4.30)$$

$$E_{AB} = \sum_{\mu}^A \sum_{\nu}^B \left(2 P_{\mu\nu} \beta_{\mu\nu} - \frac{1}{2} P_{\mu\nu}^2 \gamma_{AB} \right) \\ + \left(\frac{Z_A Z_B}{R_{AB}} + P_{AA} P_{BB} \gamma_{AB} - P_{AA} V_{AB} - P_{BB} V_{BA} \right) \quad (4.31)$$

IV-3. Choice of Parameters of CND01 and CND02

In the complete neglect of differential overlap approximation, the CND01 and CND02 methods are different levels of approximation of the equations.

The LCAOSCF Hartree-Fock matrix elements are

$$F_{\mu\mu} = U_{\mu\mu} + \left(P_{AA} - \frac{1}{Z} P_{\mu\mu} \right) \gamma_{AA} + \sum_{B \neq A} (P_{BB} \gamma_{AB} - V_{AB}) \quad (4.28)$$

$$F_{\mu\nu} = \beta_{AB}^{\circ} S_{\mu\nu} - \frac{1}{Z} P_{\mu\nu} \gamma_{AB} \quad (\mu \neq \nu) \quad (4.29)$$

where the bonding parameter β_{AB}° is given by

$$\beta_{AB}^{\circ} = 0.5 (\beta_A^{\circ} + \beta_B^{\circ}) \quad (4.32)$$

In the equation (4.32), β_A° is chosen empirically but depends only on the nature of atom A. These values are listed in Table 2. The parameters $U_{2S,2S}$ and $U_{2P,2P}$ can be estimated from ionization potentials, using the theoretical value of γ_{xx} (12).

$$\begin{aligned} I_s(X, 2s^m 2p^n) &= E(X^+, 2s^{m-1} 2p^n) - E(X, 2s^m 2p^n) \\ &= -U_{2S,2S} - (m+n-1) \gamma_{xx} \end{aligned} \quad (4.33)$$

$$\begin{aligned} I_p(X, 2s^m 2p^n) &= E(X^+, 2s^m 2p^{n-1}) - E(X, 2s^m 2p^n) \\ &= -U_{2P,2P} - (m+n-1) \gamma_{xx} \end{aligned} \quad (4.34)$$

or

$$-I_\mu = U_{\mu\mu} + (Z_A - 1) \gamma_{AA} \quad (4.35)$$

and the atomic electron affinities A_μ 's are used by the formula

$$-A_\mu = U_{\mu\mu} + Z_A \gamma_{AA} \quad (4.36)$$

Also the equation (4.28) can be rewritten

$$\begin{aligned}
 F_{\mu\mu} = & U_{\mu\mu} + \left(P_{AA} - \frac{1}{2} P_{\mu\mu} \right) \gamma_{AA} \\
 & + \sum_{B \neq A} (P_{BB} - Z_B) \gamma_{AB} \\
 & + \sum_{B \neq A} (Z_B \gamma_{AB} - V_{AB}) \quad (4.28)'
 \end{aligned}$$

where the last term of equation (4.28)' is described as penetration integral contributions to $F_{\mu\mu}$.

The following table gives the approximate form between CND01 and CND02.

reference	TABLE 4	
	Difference between CND01 and CND02	
$-U_{\mu\mu}$	$I_\mu + (Z_A - 1) \gamma_{AA}$	$\frac{1}{2}(I_\mu + A_\mu) + (Z_A - \frac{1}{2}) \gamma_{AA}$ (4.37)
$F_{\mu\mu}$	$U_{\mu\mu} + (P_{AA} - \frac{1}{2} P_{\mu\mu}) \gamma_{AA}$ $+ \sum_{B \neq A} (P_{BB} \gamma_{AB} - V_{AB})$	$U_{\mu\mu} + (P_{AA} - \frac{1}{2} P_{\mu\mu}) \gamma_{AA}$ $+ \sum_{B \neq A} (P_{BB} - Z_B) \gamma_{AB}$ (4.38)

Where 1 the average ionization potentials I_μ (e.v.) used to fix $U_{\mu\mu}$ are listed in Table 3.
 2 the matrix elements $\frac{1}{2}(I_s + A_s)$ and $\frac{1}{2}(I_p + A_p)$ are listed in Table 5.

TABLE 5							
Matrix Elements From Atomic Data (e.v.)							
H	Li	Be	B	C	N	O	F
$\frac{1}{2}(I_a + A_a)$	7.176	3.106	5.946	9.594	14.051	19.316	25.390
$\frac{1}{2}(I_p + A_p)$		1.258	2.563	4.001	5.572	7.275	9.111
							32.272
							11.080

If the penetration integral term in equation (4.28)' was neglected to avoid the excess bonding and high value of force constants, then equation (4.28)' can be reduced to the form of (4.38). This corresponds to substituting the following term for CND02 from CND01:

$$V_{AB} = Z_B \gamma_{AB} \quad (4.39)$$

Using parameters specified in the above way, the LCAOSCF equations are solved in the following steps:

- (a) An initial set of M.O. coefficients $C_{i\mu}$ is obtained from a "Hückel type" calculation such that $F_{\mu\mu}$ is replaced by average ionization potential and $F_{\mu\nu}$ by $\beta^* S_{\mu\nu}$.
- (b) Electrons are assigned in pairs to the M.O.'s with lowest energies.
- (c) Calculated $P_{\mu\mu}$ and $P_{\mu\nu}$ are used to form a new Hartree Fock matrix element $F_{\mu\nu}$.
- (d) New coefficients $C_{i\mu}$'s are derived from this $F_{\mu\nu}$ and the process is repeated from step (b) until self-consistency is achieved on all coefficients with a tolerance of 0.0001.

V. Discussion of Results

The molecules selected for these calculations are as follows:

Hydrogen molecule (H_2), Lithium molecule (Li_2), Beryllium (Be_2), Nitrogen molecule (N_2), Fluorine molecule (F_2), water molecule (H_2O), Ammonia molecule (NH_3), Ethane molecule (C_2H_6), oxygen difluoride (F_2O), Difluorodiazine (N_2F_2), Methane (CH_4), Methylfluoride (CH_3F) and Hydrogen Peroxide (H_2O_2). These calculations will show the minimum configurations for bond lengths, bond angles, force constants, the

energy level considerations for NH_3 and F_2O , and the Barrier for NH_3 , C_2H_6 , N_2F_2 and H_2O_2 . Finally the calculations will extend the variation of parameters to fit the experimental potential surfaces.

V-1. Comparison of the equilibrium configurations and force constants

The ASCFT calculations with various inter-nuclear distances and bond angles are useful in predicting equilibrium bond lengths and bond angles. These results are listed in Table 6. The equilibrium configurations (bond lengths and bond angles) are in fairly good agreement with experimental values but the force constants are too high compared with the experimental values by a factor of about 2.0. This can be improved by adjusting parameters, such as the Slater exponent and β° .

Sample results are discussed in Section V-9.

TABLE 6 Comparison of Bond Lengths, Bond Angles & Force Constants (k_r & k_θ)							
	Bond Length (A°) ⁽¹³⁾		Bond Angle (deg)		(13)Force Consts		(k_r : 10^5 dyne/cm k_θ : 10^{11} erg/rad. ²)
	Cal.	Obs.	Cal.	Obs.	Cal.	Obs.	
H ₂	0.7459	0.7415			10.143	5.6	(14)
N ₂	1.1395	1.0976			52.160	23.10	
H ₂ O	1.0289	0.958	104.22	104.45	17.260 0.845	8.23 0.694	(14)
NH ₃	1.0657	1.015			14.68	6.86	(14)
CH ₄	1.1135	1.1135			12.65	5.45	
			109.47	109.47		0.498	(15)
C_2H_6 D_{3d}^2 LCH	R _{CH}	1.1195	1.102		12.12	5.35	
	R _{CC}	1.4633	1.543		16.34	4.57	
			107.76	109°37'		0.51	(16)
			110.86	109°37'		0.63	

V-2. Water molecules (H_2O)

For H_2O , C_{2v} symmetry was assumed with an O-H bond length of 0.96\AA° . The first calculation shows an energy minimum at a bond angle of 107.28° . At this bond angle, the equilibrium O-H bond length of 1.0289\AA° is obtained. With this bond length, the second calculation shows the bond angle of 104.22° at which the O-H bond length is calculated to be 1.0289\AA° . This is in satisfactory agreement with the experimental bond angle of 104.45° (13). These calculations demonstrate the O-H bond stretching and angle HOH bending motion such that the O-H bond lengths tend to have symmetrical stretching motion and the bond angle tends to have scissoring motion (symmetrical in-plane deformation). A series of these calculations is listed in Table 7. The stretching force constant is calculated to be 17.26×10^5 (dyne/cm) which is higher by a factor of 2.1 with respect to the experimental value of 8.23×10^5 (dyne/cm). The bending force constant is calculated to be 0.845×10^{-11} (erg/rad²) which is higher by a factor of 1.22 than the experimental value of 0.694×10^{-11} (erg/rad²) (14).

TABLE 7

	Calculation I	Calculation II	Experiment
$R_{\text{OH}}(\text{\AA}^\circ)$	0.96 (Exp)	1.0280	0.958
$\angle \text{HOH}$	107.28	104.22	104.45

* The computer outputs (sample) are listed in Appendix 2.

V-3. Ammonia Molecule (NH_3)

The ammonia molecule with an NH bond length of 1.05\AA° (13) is calculated to be non-planar with an $\angle \text{HNH}$ bond angle of 106.825°

which is in close agreement with the experimental value of 106.6° (13). At this value of the bond angle, the NH bond length was found to be 1.0657 \AA° . The subsequent calculation shows a bond angle of 104.86° and again the bond length of 1.0673 \AA° . On the other hand the equilibrium bond length for the planar configuration gives 1.0543 \AA° . It is interesting when calculations presented here are compared with results recently calculated by R. Moccia and L. Randaccio (17). They reported the minimum bond length of 1.878 a.u. (0.9938 \AA°) at a bond angle of $105^\circ 36'$ and a bond length of 1.837 a.u. (0.9721 \AA°) at a planar configuration. The change in minimum bond length between non-planar and planar configuration is 0.0217 \AA° by Moccia and 0.0114 \AA° by the ASCFT. The smaller value of this bond length change in the present calculation is due to the higher stretching force constants for ASCFT. Also, subsequent calculations can predict the symmetrical bond stretching motion and symmetrical in-plane deformation of bond angle for the ground state of this molecule. The stretching force constants are calculated to be 14.64×10^5 (dyne/cm). This differs by a factor of 2.14 with respect to the experimental value of 6.86×10^5 dyne/cm (14) and the bending force constants are calculated to be 0.95×10^{-11} erg/rad.² (factor of 1.58 with respect to experimental values of 0.6×10^{-11} erg/rad² (14)).

It is also interesting to compare the barriers calculated by the several methods and the difference in barriers with respect to adjusting the various parameters. These are listed in Tables 8 and 9, respectively.

TABLE 8

Comparison of the results of Calculations for NH₃

Reference	Method of calculations	R _{NH} (a.u.)	∠ HNH (deg)	Pyramid Height(a.u.)	Barrier Height(a.u.)
Present Calc.	Approximate (CNDO) SCF MO	1.9923	106°49'	0.749	0.0251
Higuchi (18)	Approximate polycenter SCF MO	1.916	108.0	0.592	0.0147
Kaplan (19)	Single Determinant polycenter SCF MO	1.916	106°47'	0.719	0.146
Moccia (20)	Single Determinant one center SCF MO	1.928	110°2'	0.6245	0.0027
Joshi (21)	Single determinant one center SCF MO	1.867	109°34'	0.626	0.0411
Moccia (17)		1.878	105°36'	0.739	0.00905
Experiment		1.9162	106°47'	0.719	0.0092 (22)

From Table 9, it is interesting to compare the change in barrier with respect to a change in bond angles at the fixed bond length of 1.0657 Å° (Calculation II and IV) such that the change in barrier is 0.000030279 a.u. (0.002540830 - 0.002510551) and the change in bond angle is 1.965° (106.825° - 104.86°). From this calculation, it is found that the calculated barrier is 0.002540830 a.u. which is different by only 1.2% from the first calculated barrier.

The electronic configuration is found to be

$$(1a_1)^2 (1e)^4 (2a_1)^2 a_1 .$$

Configurations calculated by ASCFT, EHT and full LCAOSCFT by H. D. Joshi (21) are compared in Fig. 1 and Fig 2. There is complete agreement between ASCFT and full LCAOSCFT calculations for the orbital energies as a function of height of pyramid. It is noted that the lowest orbital

FIG. 1. E_{tot} . AND E_{orb} . OF NH_3 AS FUNCTION OF PYRAMID HEIGHT.





FIG. 2. $E_{\text{tot.}}$ & $E_{\text{orb.}}$ OF NH_3 VS. PYRAMID HEIGHT
(BY EHT)



energy in LCAOSCFT calculation is due to the (1s) electron (inner-shell) of Nitrogen but ASCFT neglects that part. On the other hand, the EHT calculation (Fig. 2) does not even demonstrate a double minimum potential curve. Therefore the EHT is quite inferior for this kind of molecule.

TABLE 9

Change in Barrier for NH₃ w.r.t. minimizing the parameter

	$R_{\overline{N}H}$ (\AA°)	$\angle ZNH$	$\angle HNH$	E_{total} (a.u.)	Barrier (a.u.)
Calculation I (General)	1.02 (fixed)	o	120	-13.85761125	0.02013903
	1.02 (fixed)	112.0	106.825	-13.87775028	
Calculation II (Equilibrium)	1.0543	o	120	-13.86430636	0.02510551
	1.0657	112.0	106.825	-13.88941245	
III	1.0543	o	120	-13.86430636	0.02453518
	1.0543	113.18	105.10	-13.88890154	
IV	1.0657	o	120	-13.86362706	0.02608760
	1.0657	113.55	104.86	-13.88971466	
Experimental		112.206	106.6		0.0092
* The true Barrier for this calculation is (13.88971466 - 13.86430636) (a.u.)					0.02540830

V-4. Ethane molecule (C_2H_6)

Calculations based on ASCFT and EHT have been carried out for Ethane in both eclipsed and staggered configurations with experimental values such that $R_{\overline{CC}} = 1.543 \text{\AA}^\circ$, $R_{\overline{CH}} = 1.102 \text{\AA}^\circ$ and $\angle CCH = 109^\circ 37'$ (tetrahedral angle). The first calculation shows the equilibrium angle for both eclipsed and staggered forms using EHT and ASCFT. The energy then was minimized by varying the bond length $R_{\overline{CC}}$, and finally by varying bond length $R_{\overline{CH}}$. The stretching force constants ($k_{\overline{CC}}$ and $k_{\overline{CH}}$) were found and those values are listed in Table 10.

It is of interest to look at the barrier resulting in the change in geometry. These changes in parameters and the corresponding barriers are compared in Table 11. These comparisons show that the eclipsed form is more open than the staggered form by a few tenths of a degree; also the bond length R_{CC} is elongated a few thousandths of an Ångstrom and the bond length R_{CH} is shortened a few ten thousandths of an Ångstrom. Some researchers have shown an elongation for R_{CH} . Although these changes (R_{CH}) in geometry are small, their effect on the internal-rotation barrier is very significant.

TABLE 10

Comparison of Ethane Betn. EHT & ASCFT Calculation

Reference	Calculated				Expt. (16) D3d
	ASCFT		EHT		
	Eclipsed	Stagger	Eclipsed	Stagger	
$\angle CCH$	111.28	110.86	110.99	110.44	109°37'
$\angle HCH$	107.60	108.04	107.90	108.48	109°37'
R_{CC}	1.4660	1.4633	1.8070	1.8000	1.543
R_{CH}	1.1193	1.1195	0.9086	0.9088	1.102
$k_{CCH} [10^{11}]$ <small>erg/rad.</small>	(1.74)	(1.67)	(8.85)	(8.8)	0.63
$k_{HCH} [10^5]$ <small>dyne/cm</small>	()	()	()	()	0.51
$k_{CC} [10^5]$	15.887	16.340	197.0	184.0	4.57
$k_{CH} [10^5]$	12.125	12.124	164.05	186.56	5.35
Barrier (kcal/mole)		2.3288		2.6586	$2.875^{+0.125}_{-0.125}$ (23)

There is some uncertainty in the Table 11 for EHT calculation. Every reported calculation scheme has the same tendency to increase the barrier when the parameters are changed in sequence, but EHT

calculation shows the barrier is decreased. The resultant barrier by EHT is 1.6358 kcal/mole. This is not in agreement with the value 2.6586 kcal/mole found by varying only one parameter, $\angle CCH$, holding the other two parameters R_{CC} and R_{CH} constant. It is noted that R. Hoffmann (1) reported 4.0 kcal/mole with a Slater exponent (H) of 1.0. Present calculations use the value of 1.2. However the results are in fairly good agreement with experimental values using both ASCFT and EHT (with some uncertainty).

TABLE II
Comparison of Barrier for Ethane

Reference	\triangle Parameter(Ecl.—Stag)			Barrier(Eclip.—Stag)		
	$\angle CCH$ (deg)	R_{CC} (\AA°)	R_{CH} (\AA°)	$\angle CCH$	R_{CC}	R_{CH}
T.L.Hill (24) (1948)	0.34	0.0054	0.0002	0.613	0.665	0.700
L.S. Bartell (25) (1960)	0.20	0.0029	0.0001	0.367	0.383	0.394
J.T.Vanderslice (26) & E.A.Mason(1960)	0.17	0.0024	-0.0001	0.387	0.416	0.434
L.Salem (27) (1962)	0.05	0.0007	0.0000	0.104	0.106	0.107
K.E.Howlett (28) (1960)	0.40	0.0059	-0.0002	0.779	1.108	1.298
V.Magnasco (29) (1962)	0.55	0.0080	-0.0011	-1.532	1.675	2.944
O.J.Sovers & (30) M.Karplus (1966)	0.20	0.0029		2.311	3.611	
Present (ASCFT)	0.42	0.0027	-0.0002	1.8637	2.2848	2.3288
(EHT)	0.55	0.0070	-0.0002	2.6586	1.5746	1.6358
Expt.	3.03 ± 0.3 (kcal/mole) (31)			2.875 ± 0.125 (kcal/mole) (23)		

V-5. Methane (CH_4) and Methylfluoride (CH_3F)

Calculations between methane and methylfluoride were carried out using tetrahedral symmetry for methane and $\text{C}3\text{v}$ symmetry for methylfluoride with $R_{\overline{\text{CH}}} = 1.1135\text{A}^\circ$ for CH_4 and $R_{\overline{\text{CH}}} = 1.109$ and $R_{\overline{\text{CF}}} = 1.385$ for CH_3F . The calculated values for the equilibrium configurations are listed in Table 12. The force constants are calculated for each molecule and these are listed in Table 12. The stretching force constants are different by a factor of 2.3 for CH_4 and 2.5 for CH_3F with respect to their observed values (15).

For a methane molecule, the calculated bond lengths and bond angles are the same as the observed values.

For methylfluoride molecules, the bond angle $\angle \text{HCH}$ is more open than the angle of $\angle \text{HCF}$ which can be explained as follows: there exists rehybridization for the CH_3F molecule because there must be more P-character in C-F bond due to the electron withdrawing fluorine; on the other hand, there must be more S-character in C-H bond which gives more SP^2 hybrid character for the C-H sigma (σ) bonds. It is obvious that the SP^2 hybrid orbital is more planar than SP^3 . Therefore $\angle \text{HCH}$ is more open. It is here that the best agreement between theoretical and calculated results was found.

TABLE 12

Comparison of r , θ and k_r & k_e between CH_4 & CH_3F

	Bond Length (\AA°)		Bond Angle (deg)		Force Consts.	
	Cal.	Obs.	Cal.	Obs.	Cal.	Obs.
CH_4	1.1135	1.1135			12.65	5.45
			109.47	109.47	(.745)	0.498
R_{N}	1.1180	1.109			12.09	4.71(15)
R_{F}	1.3458	1.385			23.57	5.64(15)
$\text{CH}_3\text{F}_{2\text{HCH}}$			110.382	109.997		0.443(15)
$\angle \text{FCCH}$			108.54	108.94	(1.77)	0.792(15)

V-6. Difluorodiazine (N_2F_2)

Calculations have been carried out for difluorodiazine in both trans and Cis configurations with $R_{\text{NN}} = 1.25\text{\AA}^\circ$, $R_{\text{NF}} = 1.44\text{\AA}^\circ$ and $\angle \text{NNF} = 115^\circ$ (13). In both configurations, the new equilibrium distances and bond angles are determined and are listed in Table 14. When comparisons are made of the equilibrium geometry in Table 14, the bond angle $\angle \text{NNF}$ is more open for Cis than trans configurations. Significantly, the bond length R_{NN} is elongated a few thousandths more for trans than Cis (same for R_{NF}).

It is of interest to compare the energy level difference between Cis and trans configurations. The experimental results giving the stability between both configurations are listed in Table 13. In 1963, Armstrong and Marantz published that the Cis form is more stable by 3.0 ± 0.3 kcal/mole (36) (refer also (37)). The present calculation predicts the Cis form to be more stable by 3.249 kcal/mole than the trans (C_2h) form. Fortunately, these results are in most satisfactory

agreement with experimental value. In Table 14 are compared the differences in energies between the Cis and trans configurations for a variation in molecular parameters. First the angle \angle_{NNF} was varied to minimize the energy. With this bond angle, the minimum bond length R_{NN} was calculated and finally the minimum bond length R_{NF} was found. In each case, the difference in energies was compared with the one obtained initially. It was found that there is no effect due to varying the angle \angle_{NNF} and bond length R_{NN} but there is a very significant difference when the bond length R_{NF} was minimized. This result shows the configuration is affected significantly due to the R_{NF} stretching motion.

Year	TABLE 13		
	Author	Reference	Results
1947	S.H. Bauer (32)	J.Am.Chem.Soc., 69, 3104	trans is more stable than Cis configuration
1959	C.B. Colburn, et.al. (35)	" " " , 81, 205	
1960	R.H. Sanborn (34)	J.Chem.Phys., 33, 1855	Cis and $N=N<^{\text{F}}$ is more chemically active isomer
1961	R. Ettinger, et.al. (35)	" " " , 34, 2187	
1963	G.T. Armstrong & S. Marantz (36)	J.Chem.Phys., 38, 169	Cis is more stable by 3.0 ± 0.3 kcal/mole
Present			Cis is more stable by 3.249 kcal/mole

The next interesting calculation is the barrier due to the rotational motion which was reported by the Binenboym (37). It was reported by experiment to be 32.0 kcal/mole and calculated to be 84 kcal/mole (36) between trans and linear configuration. However, the present calculations were carried out in various ways and those results are listed in Table 15. The calculated barrier between linear and trans form in

TABLE 14

Equilibrium Configuration Bn. C_{2v} & C_{2h} for N_2F_2


Calculation	Parameters			Δ Par ($C_{2v} - C_{2h}$)		Diff. in Barrier	
	$\angle NNF$ (deg)	R_{NN} (A°)	R_{NF} (A°)	$\angle NNF$	R_{NN}	R_{NF}	$\Delta E (C_{2v} - C_{2h})$
I General	115	1.25	1.44	0	0	0	0.2553 (0)
	115	1.25	1.44				
II	C_{2v}	109.98	1.25	1.44	5.89	0	0.2553 (0)
	C_{2h}	104.09	1.25	1.25			
III	C_{2v}	109.98	1.2197	1.25	5.89	-0.0021	(-)0.04962 (.31)
	C_{2h}	104.09	1.2218	1.25			
IV	C_{2v}	109.98	1.2197	1.2410	5.89	-0.0021	(-)3.2492 (3.5)
	C_{2h}	104.09	1.2218	1.2441			
Expt. value							(-)3.0±0.3

Table 15 is too high with respect to the reported barrier but the calculation between trans and C_2 form shows a satisfactory agreement with the calculated (38) and experimental value (39). It must be noted that when an attempt was made to calculate the rotational barrier, no dihedral angle exists; that is, when the dihedral angle is 90 degrees, the bond angle $\angle NNF$ turns out linear, and also the dihedral angle does not exist and the motion is predicted to be an up and down motion which is shown in Calculation IV and V in Table 15. The calculated barriers are illustrated in Fig. 3.

TABLE 15

Comparison of Barrier for N_2F_2

No.	Ref.	Parameters			Etot. (a.u.)
		$\angle NNF$	R _{NN}	R _{NF}	
I	C _{2v} (Cis)	109.98	1.2197	1.2410	-78.87407234
II	C _{2h} (trans)	104.09	1.2218	1.2441	-78.86889607
III	0.5(I + II)	107.035	1.22075	1.24255	-78.87148421
IV	C ₂ (__)	114.07	1.2208	1.2426	-78.75824577
V	C _{2v} (---)	180.0	1.2119	1.440*	-78.54333813
Barrier	E(II) - E(IV) = 69.456	E(II) - E(IV) = 204.356	E(I) - E(IV) = 72.7057	E(I) - E(V) = 207.657	kcal/mole
	Exp.	E(II) -- E(V) = 32 kcal/mole (37)			
	Cal.	E(II) -- E(V) = 84 kcal/mole (36)			


Fig. 3 Barrier for N_2F_2 as function of XNF

V-7. Oxygen difluoride (F_2O)

For the F_2O molecule with C_{2v} symmetry ($R_{OF} = 1.41\text{ \AA}^\circ$ (13)), the lowest energy configuration is calculated to be bent with an $\angle FOF = 97.16^\circ$ (at fixed $R_{OF} = 1.50\text{ \AA}^\circ$) as compared with the experimental angle of 103.80° (38). The bond length R_{OF} (at angle of 97.16°) is calculated to be 1.1792 \AA° . Also the bending and stretching force constants are calculated to be $1.1497 \times 10^{-11} \text{ erg/rad}^2$ (observed $K_{FOF} = 0.55 \times 10^{-11} \text{ erg/rad}^2$) and $40.94 \times 10^5 \text{ dyne/cm}$ (observed $K_{OF} = 5.57 \times 10^5 \text{ dyne/cm}$ (14)).

It is of interest to compare the orbital energies as a function of internuclear angle with that published by Buenker and Peyerimhoff (39). The calculated results are illustrated in Fig. 4 and these were compared with calculations by Buenker and Peyerimhoff (using full LCAOSCF theory) also in Fig. 4. The comparison in Fig. 4 shows a satisfactory agreement except for $5a_1$, $1b_1$ and $3b_2$. It is noted that, in full LCAOSCF calculation, the lowest doubly degenerate orbitals (due to $1s$ electrons of two Fluorines) and the next singly degenerate orbital (due to the $1s$ electron of Oxygen) were neglected. Therefore the comparison is valid starting with the third level in the Fig given by Buenker.


FIG. 4. ORBITAL ENERGY OF F_2O AS FUNCTION OF $\angle \text{EOF}$.



V-8. Hydrogen Peroxide (H_2O_2)

For the hydrogen peroxide molecule, the calculations were performed to find the barrier and the equilibrium configurations with $R_{\overline{OH}}=0.97\text{\AA}^\circ$, $\angle HOO=100^\circ$, $R_{\overline{OO}}=1.49\text{\AA}^\circ$ and dihedral angle of 93.6° (13). Unfortunately, the present calculation does not show the existence of a dihedral angle. The result of the calculation shows that there exists a Cis and trans configuration for H_2O_2 just as for N_2F_2 . The structural parameters are illustrated in Fig. 5.

Fig. 5 Structural Parameters (H_2O_2)



V-9. Homonuclear diatomic molecules

For the diatomic molecules, the equilibrium configurations of H₂, Li₂, N₂ and F₂ were calculated. An attempt was made to find a new set of optimized parameters by changing the Slater exponents and beta zeroes (β°). The equilibrium bond lengths and force constants are listed in Table 16. It is noted that Be₂, C₂ and O₂ molecules are excluded in the calculations because they are ground state triplets, and the Be₂ molecule is non-bonded. The necessary partial derivatives were found and listed in Table 16.

TABLE 16

Equilibrium Configurations and Some Partial derivatives
for homo nuclear diatomic molecules

Re (A°)		$k_r (10^5 \text{ dyne/cm})$		average partial between (S.E.) $_{\pm 0.1}$ and also $\beta^\circ \pm 1.0$			
Cal.	Obs.	Cal.	Obs.	$(\partial R / \partial S)_S$	$(\partial R / \partial \beta^\circ)_S$	$(\partial k_r / \partial S)_{\beta^\circ}$	$(\partial k_r / \partial \beta^\circ)_S$
H ₂	0.746 (0.89)	0.74	10.14 (6.5)	5.6	-0.54	-0.34	19.18
Li ₂	2.179 (2.788)	2.67	0.84 (0.41)	0.25	-2.94	-0.022	3.07
N ₂	1.14	1.09	52.16	23.10	-0.47	-0.01	61.06
F ₂	1.12	1.44	56.41	4.45			2.34

For those molecules, an attempt was made to find a new set of optimized parameters fitting experimental equilibrium bond lengths and force constants. The Slater exponent and β° were considered in adjusting the parameters to optimize agreement for calculated potential surfaces. The procedures used to find a new set of Slater exponents and beta zero (β°) were as follows:

First: Change the Slater exponent by ± 0.1 and beta zero by ± 1.0 ,
then find the calculated equilibrium bond length and force constant.

Second: Find the partial derivatives

$$\left(\frac{\partial R}{\partial S}\right)_{\beta^o}, \left(\frac{\partial k_r}{\partial S}\right)_{\beta^o}, \left(\frac{\partial R}{\partial \beta^o}\right)_S \text{ and } \left(\frac{\partial k_r}{\partial \beta^o}\right)_S$$

where "S", stands for Slater exponent.

Third: Find the new Slater exponent and by following equations:

$$dR = \left(\frac{\partial R}{\partial S}\right)_{\beta^o} dS + \left(\frac{\partial R}{\partial \beta^o}\right)_S d\beta^o \quad (5.1)$$

$$dk_r = \left(\frac{\partial k_r}{\partial S}\right)_{\beta^o} dS + \left(\frac{\partial k_r}{\partial \beta^o}\right)_S d\beta^o \quad (5.2)$$

then approximate the dR , dS and $d\beta^o$ as follows:

$$dR \approx \Delta R = R_{\text{req}} - R_{\text{cal}}$$

$$dS \approx \Delta S = S_{\text{new}} - S_{\text{cal}}$$

$$d\beta^o \approx \Delta \beta^o = \beta^o_{\text{new}} - \beta^o_{\text{cal}} \quad (5.3)$$

Fourth: Solve equation (5.1) and (5.2) to find the new Slater exponent and β^o . For example:

(1) H₂ molecule:

$$\begin{bmatrix} -0.06 \\ -4.83 \end{bmatrix} = \begin{bmatrix} -5.4 & -3.4 \\ 19.18 & 1.055 \end{bmatrix} \rightarrow \begin{bmatrix} -0.277 \\ 0.457 \end{bmatrix} = \begin{bmatrix} \Delta S \\ \Delta \beta^o \end{bmatrix}$$

therefore

$$S_{\text{new}} = 0.923$$

$$\beta^o_{\text{new}} = 9.457 \quad (5.4)$$

(2) Li₂ case:

$$\begin{bmatrix} -0.49 \\ -0.59 \end{bmatrix} = \begin{bmatrix} 2.94 & 0.022 \\ 3.07 & 0.52 \end{bmatrix} \rightarrow \begin{bmatrix} -0.164 \\ -0.410 \end{bmatrix} = \begin{bmatrix} \Delta S \\ \Delta \beta^o \end{bmatrix}$$

therefore

$$S_{\text{new}} = 0.49$$

$$\beta^o_{\text{new}} = 8.59 \quad (5.5)$$

(3) N₂ case:

$$\begin{bmatrix} -0.05 \\ -29.06 \end{bmatrix} = \begin{bmatrix} -0.47 & -0.01 \\ 61.06 & 2.34 \end{bmatrix} \rightarrow \begin{bmatrix} 0.87 \\ -35.5 \end{bmatrix} = \begin{bmatrix} \Delta S \\ \Delta \beta^o \end{bmatrix}$$

therefore

$$S_{\text{new}} = 2.87$$

$$\beta^o_{\text{new}} = -9.5 \quad (5.6)$$

From these results, (5.4) and (5.5) are consistent but (5.6) is completely inconsistent because the force constant is too high.

Fifth: Finally, repeat the calculation using the above new set of input parameters (S_{new} and $\beta^{\circ}_{\text{new}}$). The result for the H_2 and Li_2 molecules are listed in parentheses in Table 16.

VI. CONCLUSION

The Approximate Self-Consistent Field M.O. theory was applied to the calculation of electronic structure for several selected molecules and these results were compared with results by full LCAOSCFT calculations, if they were available. The most important features of these calculations are to predict equilibrium configurations (bond length and bond angle) and the barrier by the variation of internuclear distances and angles using the ASCFT. The EHT calculations are limited to hydrocarbons which give good results (refer to calculation of Ethane molecule). In general, the barrier predicted by ASCFT calculation is in satisfactory agreement with the experimental value.

An attempt was made to find a new set of input parameters (Slater exponent and β°) to improve the prediction of potential surfaces for certain homonuclear diatomic molecules but the attempt failed except for the H_2 and Li_2 molecules (see Table 16).

The features of Potential Surfaces of molecules can be predicted with the approximate self-consistent field theory. Qualitatively, the agreement between calculations and experimental observations is quite good. It is conceivable that, with the adjustment of certain parameters

such as resonance integrals (β^o), Slater exponents and penetration integrals, quantitative agreement with experimental results can be obtained.

BIBLIOGRAPHY

- (1) R. Hoffmann, J. Chem. Phys., 39, 1937 (1963)
- (2) J.A. Pople, D.P. Santry and G.A. Segal, J. Chem. Phys., 43, S129 (1965)
- (3) J.A. Pople and G.A. Seagal, J. Chem. Phys., 43, S136 (1965)
- (4) J.A. Pople and G.A. Seagal, J. Chem. Phys., 44, 3289 (1966)
- (5) J.C. Slater, Phys. Rev., 36, 57 (1930)
- (6) H.A. Skinner and H.O. Pritchard, Chem. Rev., 55, 745 (1955)
- (7) R.S. Mulliken, J. Chim. Phys., 46, 497, 675 (1949)
- (8) M. Wolfsberg and L. Helmholtz, J. Chem. Phys., 20, 837 (1952)
- (9) R.S. Mulliken, C.A. Rieke, D. Orloff and H. Orloff, J. Chem. Phys., 17, 1248 (1949)
- (10) C.C.J. Roothaan, Rev. Mod. Phys., 23, 69 (1951)
- (11) Hartree Fock, Proc. Cambridge Phil. Soc., 24, 83, 111, 426 (1928)
- (12) C.C.J. Roothaan, J. Chem. Phys., 19, 1445 (1951)
- (13) Tables of interatomic distance and Configurations in molecules and ions, The Chemical Society, London, 1965
- (14) G. Herzberg, Infrared and Raman Spectra, D. Van Nostrand Co., Inc., Princeton, New Jersey, 1945
- (15) J.W. Linnett, J. Chem. Phys., 8, 91, (1940)
- (16) G.E. Hansen and D.M. Dennison, J. Chem. Phys., 20, 313 (1952)
- (17) R. Moccia and L. Randaccio, J. Chem. Phys., 45, 4303 (1966)
- (18) J. Higuchi, J. Chem. Phys., 24, 535 (1956)
- (19) M. Kaplan, J. Chem. Phys., 26, 1074 (1957)
- (20) R. Moccia, J. Chem. Phys., 40, 2164; 2176; 2186 (1964)
- (21) H.D. Joshi, J. Chem. Phys., 43, S40 (1965)
- (22) J.D. Swalen and J.A. Ibers, J. Chem. Phys., 36, 1914 (1962)

(23) E.B. Wilson, Advances in Chem. Phys., 2, 367 (1959)

(24) T.L. Hill, J. Chem. Phys., 16, 399 (1948)

(25) L.S. Bartell, J. Chem. Phys., 32, 827 (1960)

(26) J.T. Vanderslice and E.A. Mason, J. Chem. Phys., 33, 492 (1960)

(27) L. Salem, J. Chem. Phys., 37, 2100 (1962)

(28) K.E. Howlett, J. Chem. Soc., 4357 (1957), 1055 (1960)

(29) V. Magnasco, NUOVO Cimento., 24, 425 (1962)

(30) O.J. Sovers and M. Karplus, J. Chem. Phys., 44, 3033 (1966)

(31) D.R. Lide, J. Chem. Phys., 29, 1426 (1958)

(32) S.H. Bauer, J. Am. Chem. Soc., 69, 3104 (1947)

(33) C.B. Colburn. et al., J. Am. Chem. Soc., 81, 205 (1959)

(34) R.H. Sanborn, J. Chem. Phys., 33, 1855 (1960)

(35) R. Ettinger, et al., J. Chem. Phys., 34, 2187 (1961)

(36) G.T. Armstrong and S. Marantz, J. Chem. Phys., 38, 169 (1963)

(37) J. Binenboym, A. Burcat, A. Lifshitz and J. Shamir, J. Am. Chem. Soc., 88, 5039 (1966)

(38) J.A. Ibers and V. Schomaker, J. Phys. Chem., 57, 699 (1953)

(39) R.J. Buenker and S.D. Peyerimhoff, J. Chem. Phys., 45, 3682 (1966)

(40) T.Y. Wu, Vibration Spectra and Structure of Polyatomic Molecules
(National University of Peking, Kun-ming China, (1939))

(41) F.A. Cotton, Chemical Application of Group Theory (Wiley, New York, 1964)

(42) E. Cartmell and G.W.A. Fowles, Valency and Molecular Structure
(Butterworths, London, 1961)

(43) C.J. Ballhausen and H.B. Gray, Molecular Orbital Theory (Benjamin, New York, 1964)

(44) A. Streitwieser, Jr., Molecular Orbital Theory for Organic Chemist
(Wiley, New York, 1961)

(45) C. Sandorfy, Electronic Spectra and Quantum Chemistry (Prentice-Hall, New Jersey, 1964)

(46) E.B. Wilson, Jr., J.C. Decium and P.C. Cross, Molecular Vibrations
(McGraw-Hill, New York, 1955)

(47) T.M. Dunn, D.S. McClure and R.G. Pearson, Crystal Field Theory
(Harper & Row, New York, 1965)

(48) R.G. Parr, The Quantum Theory of Molecular Electronic Structure
(Benjamin, New York, 1963)

(49) E.T. Browne, Introduction to the Theory of Determinants and Matrices (William Byrd, Virginia, 1958)

APPENDIX

I Computer program for Approximate Self-Consistent Field Theory (ASCFT)

-COUP, YUN DUX 41, 3/13/23, 20, 2020.
-FTN,E,L,P.

PROGRAMM DURCH

DIMENSION IPT(5), Z(18), ZS(18), UTA(40), U(40), COORD(3,18),
1F(4,40), S(40,40), C(40,40), P(40,40), COS(2,18,18), PA(18),
2V(18,18), G(18,18), E(18,18), RAD(18,18), RHO(18,18), TAU(18,18),
3ISTP(18), AL(18), TH(18), PH(18), BONDL(18), AW(18),
4PP(40,40), PB(18)

C THIS IS A DYNAMIC PROGRAM WHICH FIRST CALLS FOR INPUT DATA AND
C THEN PERFORMS THE CND0/2 OPERATIONS

1 CALL INPUT (N,NH,NC,IPT,LIST,AL,TB,PH,BONDL,Z,ZS,SETA,U,COORD,AW)
CALL CND0 (N,NH,NC,IPT,LIST,AL,TB,PH,BONDL,Z,ZS,SETA,U,COORD,F,S,C,P,COS,PA,V,
1VAL,RHO,TB,U,PP,PD)
GO TO 1

END

SUBROUTINE CND0 (N,NH,NC,IPT,Z,ZS,BETA,U,COORD,F,S,C,P,COS,PA,V,
1G,É,ET,RAD,RHO,TAU,PP,PD)
DIMENSION IPT(5), Z(18), ZS(18), UTA(40), U(40), COORD(3,18),
1F(4,40), S(40,40), C(40,40), P(40,40), COS(3,18,18), PA(18),
2V(18,18), G(18,18), E(18,18), RAD(18,18), RHO(18,18), TAU(18,18),
3PP(40,40), PB(18)

C N IS THE NUMBER OF ATOMS IN THE MOLECULE
C NH IS THE NUMBER OF HYDROGEN ATOMS IN THE MOLECULE
C NO IS THE NUMBER OF ORBITALS WHICH OCCUPY ELECTRONS
C IPT(1) = 1 IF COORDINATES, ELECTION COEFFICIENTS, THE DISTANCE MATRIX,
C THE RADIAL MATRIX, THE TWO MATRICES, THE OVERLAP MATRIX, THE F MATRIX,
C THE SPINOR MATRIX, AND THE V MATRIX IS TO BE PRINTED OUT. IF NO
C PRINT OUT OF THESE IS DESIRED, SET IPT(1) = 0
C FOR IPT(1) GREATER THAN 1, SUCCESSIVE PRINTOUTS WILL OCCUR, DETAILING
C THE ITERATION PROCESS FOR EACH ITERATION
C IPT(2) IS NOT USED

C IPT(3) SET THIS = 0 FOR A CLOSED SHELL MOLECULE. IF IPT(3) = 1,
C ONE ELECTRON WILL BE REMOVED FROM HIGHEST OCCUPIED ORBITAL (RADICAL),
C IF IPT(3) = 2, A CND0/2 CALCULATION WILL BE FOR SEPARATE MATRICES
C FOR ALPHA AND BETA SPINS (FOR FREE RADICALS AGAIN).
C IPT(4) = 1 FOR CND0/1 CALCULATIONS, AND = 2 FOR CND0/2 CALCULATIONS.

```

C INITIALLY THE MAXIMUM NUMBER OF ITERATIONS THE PROGRAM WILL PERFORM
C BEFORE QUITTING. TYPICALLY THIS IS ABOUT 20.
C Z IS THE ARRAY OF CHARGES ON THE CORE
C ZS IS THE ARRAY OF SLATER EXPONENTS.
C BETA IS THE ARRAY OF DELTA ZEROS.
C U IS THE ARRAY OF IONIZATION POTENTIALS.
C COORD IS THE MATRIX OF CARTESIAN COORDINATES.
C F IS THE F MATRIX.
C C IS THE MATRIX OF EIGENVECTORS.
C P IS THE BOND ORDER, CHARGE DENSITY MATRIX.
C COS IS THE DIRECTION COSINE MATRIX.
C PA IS THE ARRAY OF ELECTRON CHARGE DENSITIES FOR EACH ATOM.
C V IS THE V-INTEGRAL MATRIX.
C G IS THE MATRIX OF GAUSS INTEGRALS.
C E IS THE ENERGY OF THE MOLECULE.
C ET IS THE ENERGY MATRIX, BREAKING DOWN THE ENERGY INTO ATOMIC
C AND INTERACTION TERMS.
C RAD IS THE INTERATOMIC DISTANCES MATRIX.
C RHO IS THE RHO MATRIX.
C TAU IS THE TAU MATRIX.
C PP AND PD ARE ARRAYS USED FOR OPEN SHELL CALCULATIONS ANALOGOUS TO
C P AND PA IN THE CLOSED SHELL CALCULATION.
C THE SUBROUTINES HAVE THE FOLLOWING FUNCTIONS
C FULL CHARGE PRELIMINARY CALCULATIONS, CONVERTING THE COORDINATE
C MATRIX AND THE SLATER DETERMINANT MATRIX INTO COS, RAD, RHO,
C TAU.
C OVERLAPS UP THE OVERLAP MATRIX GIVEN ZS, COORD, COS, RAD, RHO, AND
C TAU.
C GVAD SETS UP G AND V USING ZS, RAD, RHO, TAU, Z, AND IPT.
C INITL SETS UP THE INITIAL F MATRIX TO BE DIAGONALIZED.
C FIRST PRINTS OUR COORD, COS, RAD, RHO, TAU, S, F, G, AND V.
C HDIAG DIAGONALIZES F, GIVING EIGENVECTORS C
C PM SETS UP THE P AND PA MATRIX GIVEN C, NO, AND IPT(S).
C SETF SETS UP THE F MATRIX IN TERMS OF THE C OBTAINED ON PREVIOUS IT.
C INTER PRINTS OUT C, P, PA, AND F.
C CWORK SETS KEY = 0 IF C AND P MATRIX ELEMENTS AGREE TO WITHIN .0001.

```

C LNKRY CALCULATES THE ENERGY ELEMENTS AFTER ITERATION IS COMPLETE.
 NT = 4*(N-NH)+NH
 CALL PREL(N,COORD,COS,RAD,ZS,RHO,TAU,NH)
 CALL OVERL(N,NH,ZS,COURD,COS,RAD,Z,RHO,TAU)
 CALL OVAD(N,NH,ZS,RAD,Z,V,RHO,TAU,Z,IPT)
 CALL INITL(N,NH,BETA,U,U,F)
 IF(IPT(1) .EQ. 4,2,4
 4 CALL FRST(N,NH,COORD,COS,RHO,TAU,S,F,G,V)
 2 CONTINUE
 CALL NUDS(F,G,S,NT,NH)
 NUC = IPT(5)
 IF(IPT(3)/Z-1) 6,6,6
 6 DO 20 I = 1,NUC
 CALL PM(N,NH,NU,C,P,PA,IPT(3))
 CALL SETF(N,NH,P,PA,G,V,BETA,S,Z,F,U,IPT)
 IF(IPT(1)-1) 15,15,14
 14 WRITE (51,101)
 WRITE (51,100) (F(J),J = 1,NT)
 CALL INTLR(N,NH,C,P,PA,F)
 15 CONTINUE
 DO 16 J = 1,NT
 DO 16 K = 1,NT
 16 PP(J,K)=P(J,K)
 CALL NDIA(G(F,C,S,NT,NR))
 CALL PH(N,NH,NU,C,P,PA,IPT(3))
 CALL CONFR(N,NH,P,PP,KEY)
 IF(KEY) 20,30,20
 20 CONTINUE
 30 CONTINUE
 WRITE (51,101)
 WRITE (51,100) (F(J),J = 1,NT)
 CALL SETF(N,NH,P,PA,G,V,BETA,S,Z,F,U,IPT)
 CALL INTER(N,NH,C,P,PA,F)
 35 WRITE (51,104)
 CALL ENRGY(N,NH,P,J,G,BETA,S,Z,RAD,PA,E,ET,V,IPT)
 IF(IPT(1)+1) 33,41,39

```

39 DO 40 J = 1,N  (E(J,K), K = J,N)
40 WRITE (51,100) (E(J,K), K = J,N)
41 CONTINUE
42 WRITE (51,103) I
43 WRITE (51,102) ET
50 RETURN
50 CALL PM(N,NH,NO,C,P,PA,U)
51 IF(IPT(3)-2) 61,62,61
51 NO1 = NO-1
52 GO TO 62
52 NO1 = NO
53 CALL PM(N,NH,NO1,C,PP,PU,PU,J)
53 DO 90 I = 1,NO1
54 DO 68 J = 1,N
55 PA(J) = 0.5*(PA(J)+PB(J))
56 PB(J) = PA(J)
57 CALL SETF(N,NH,P,PA,G,V,BETA,S,Z,F,U,IPT)
58 IF(IPT(1)-1) 75,75,74
59 CALL INTER(N,NH,C,P,PA,F)
60 CALL HDIAG(F,C,U,NT,NR)
61 IF(IPT(1)-1) 77,77,76
62 WRITE (51,101)
62 WRITE (51,100) (F(J,J), J = 1,NT)
63 DO 70 J = 1,NT
64 DO 78 K = 1,NT
65 F(J,K) = P(J,K)
66 CALL PM(N,NH,NO,C,P,PA,U)
67 CALL CMPR(N,NH,F,P,KEY)
68 IF(KEY) 80,95,80
69 CALL SETF(N,NH,PP,PB,G,V,BETA,S,Z,F,U,IPT)
70 IF(IPT(1)-1) 85,85,84
71 CALL INTER(N,NH,C,PP,PB,F)
72 CALL HUIAS(F,C,U,NT,NR)
73 IF(IPT(1)-1) 87,87,86
74 WRITE (51,101)
75 WRITE (51,100) (F(J,J), J = 1,NT)

```

```

87 CALL PH(N,NH,NU1,C,P,F,PE,U)
90 CONTINUE
92 DO 96 J = 1,NT
93 DO 96 K = 1,N
94   F(J,K) = U*D*(P(J,K)-PP(J,K))
95   P(J,K) = U*D*(P(J,K)+PP(J,K))
96 DO 120 J = 1,N
120 PA(J) = PD(J)
      WRITE (51,106)
DO 97 J = 1,NT
97   WRITE (51,100) (F(J,K), K = 1,NT)
      WRITE (51,108)
DO 98 WRITE (51,100) (P(J,K), K = 1,NT)
98   WRITE (51,107)
      WRITE (51,100) (PA(J), J = 1,N)
GO TO 35
100 FORMAT (1H ,10F10•6)
101 FORMAT (17H ORBITAL ENERGIES)
102 FORMAT (1H ,F14•8)
103 FORMAT (1H ,13,1H ITERATIONS)
104 FORMAT (7H ENERGY)
105 FORMAT (24H NORMALIZED EIGENVECTORS)
106 FORMAT (20H SPIN DENSITY MATRIX)
107 FORMAT (3H PA)
108 FORMAT (2H P)
END

```

SUBROUTINE INITL(N,NH,BETA,U,S,F)
 DIMENSION BETA(40), U(40), S(40,40), F(40,40)

NT = 4*(N-NH)+NH
 DO 10 I = 1,NT
10 F(I,I) = U(I)
 DO 20 I = 1,NT
20 I = I+1
 DO 20 J = 1,NT

```

20   F(J,I) = 0.5*(BETA(I)+BETA(J))*C(I,J)
      RETURN
END

```

```

C
SUBROUTINE PM(N,NH,NC,CP,PA,IPT)
DIMENSION C(40,40), P(40,40), PA(16)
NT = 4*(N-NH)+NH
NOT = N-NH
DO 10 I = 1,NT
DO 10 J = 1,NT
P(I,J) = 0.0
DO 10 K = 1,NO
10 P(I,J) = P(I,J)+C(K,I)*C(K,J)
      ..
DO 20 I = 1,NT
DO 20 J = 1,NT
20 P(I,J) = 2.0*P(I,J)
IF(IPT) 21,25,21
21 DO 24 I = 1,NT
DO 24 J = 1,NT
24 P(I,J) = P(I,J) - C(NO,I)*C(NO,J)
DO 30 I = 1,NOT
25 ISUB = 4*I-3
ISUB4 = ISUB+3
PA(I) = 0.0
DO 30 J = 1,ISUB,ISUB4
30 PA(I) = PA(I)+P(J,J)
NCT1 = NOT+1
DO 40 I = NOT1,N
40 ISUB = I+3*NOT
PA(I) = P(ISUB,ISUB)
RETURN
END

```

```

C
SUBROUTINE SETF(N,NH,P,PA,G,V,BETA,S,Z,F,U,IPT)
DIMENSION P(40,40), PA(18), G(18,18), V(16,18), BETA(40),
         ZETA(40),

```

```

10(4,40), T(40,40), Z(18), U(40,40), IPT(5)
CALL INIT(N,NH,BETA,U,S,F)
NCT = N-NH
NS = 4*NCT
NT = NS+NH
IPT = IPT(4)
DO 10 IM = 1,NT
IF (IM-NS) 5,5,6
5 IA = (IM+5)/4
GO TO 7
6 IA = IM-3*NOT
7 F(IM,IM) = F(1,1,IA)-(Z(IA)-1.0/FIPT)*G(IA,IA),(PA(IA)-0.5*P(IM,IM))
1)*G(IA,IA)
DO 10 IB = 1,N
IF (IB-IA) 9,10,9
9 F(IM,IM) = F(IM,IM)+PA(IB)*G(IA,IB)-V(IA,IB)
10 CONTINUE
DO 40 IM = 1,NT
IM1 = IM+1
IF (IM-NS) 25,25,26
25 IA = (IM+3)/4
GO TO 27
26 IA = IM-3*NOT
27 DO 40 IN = IM1,NT
IF (IN-NS) 35,35,36
35 ID = (IN+3)/4
GO TO 37
36 IB = IN-3*NOT
37 F(IM,IN) = F(IM,IN)-U*5*P(IM,IN)*G(IA,IB)
40 CONTINUE
DO 50 I = 1,NT
I1 = I+1
DO 50 J = I1,NT
50 F(J,I) = F(I,J)
RETURN
END

```

```

C
SUBROUTINE COMPR(N,NH,C,P,KEY)
DIMENSION C(40,40), P(40,40)
NT = 4*(N-NH)+NH
DO 10 I = 1,NT
DO 10 J = 1,NT
IF(ABSF(C(I,J)-P(I,J))-0.0001) 10,10,20
10 CONTINUE
KEY = 0
GO TO 30
20 KEY = 1
30 RETURN
END
C
SUBROUTINE ENRGY(N,NH,P,U,G,BETA,S,Z,RAD,PA,E,ET,V,IPT)
DIMENSION P(40,40), U(40), G(18,18), BETA(40), S(40,40), Z(18),
1RAD(18,18), PA(18), E(18,18), V(18,18), IPT(5)
NOT = N-NH
NM = N-1
FIPT = IPT(4)
DO 40 IA = 1,N
E(IA,IA) = 0.0
IF( IA-NOT ) 15,15,16
15 IMN = 4*IA-3
IMX = IMN+3
SC TO 28
16 IMN = 3*NOT+IA
IMX = IMN
28 DO 40 IN = IMN,IMX
E(IA,IA) = E(IA,IA) + P(IN,IN)*(U(IN)-(Z(IA)-1.0/FIPT)*G(IA,IA))
DO 40 IN = IMN,IMX
40 L(IA,IA) = E(IA,IA)+0.5*(P(IN,IN)*P(IN,IN)
1 - 0.5*P(IM,IN)**2)*G(IA,IA)
40 140 IA = 1,NM
IA1 = IA+1
IF( IA-NOT ) 115,115,116

```

```

145 IMN = 4*IA-3
IMX = IMN+3
GO TO 118
116 IMN = 3*NOT+IA
IMX = IMN
118 DO 140 IB = IA1,N
IF (IB-NOT) 125,125,126
125 INN = 4*I B-3
INX = INN+3
GO TO 126
126 INN = 3*NOT+IB
INX = INN
128 L(IA,IB) = L(IA)*L(IB)/RAD(IA,IB)
1 - PA(IB)*V(IB,IA)
DO 140 IM = INN,IAX
DO 140 IN = INN,INX
140 E(IA,IB) = E(IA,IB) + P(IM,IN)*(BETA(IM)+BETA(IN))*S(IM,IN)
1 - •5*P(IM,IN)**2*G(IA,IB)
DO 141 I = 1,N
141 I = I+1
DO 141 J = 11,N
141 E(J,I) = 0.0
ET = 0.0
DO 80 I = 1,N
DO 80 J = 1,N
80 ET = ET+E(I,J)
RETURN
END

```

C

```

SUBROUTINE FRST(N,NH,COORD,COS,RAD,RHO,TAU,S,F,G,V)
DIMENSION COORD(3,18), COS(3,18,18), RAD(18,18), RHO(18,18),
1 TAU(18,18), S(40,40), F(40,40), G(18,18), V(18,18)
NT = 4*(N-NH)+NH
WRITE(51,100)
DO 10 I = 1,N
10 WRITE(51,120) (COORD(J,I), J = 1,3)

```

```

      WRITE (51,101)
DO 20 I = 1,N          COS(I,J,K), K = 1,N)
DO 20 J = 1,N          WRITE (51,120)
      WRITE (51,102)          (COS(I,J,K), K = 1,N)
      WRITE (51,103)
DO 25 I = 1,N          WRITE (51,120) (RAD(I,J), J = 1,N)
      WRITE (51,104)
DO 26 I = 1,N          WRITE (51,120) (RHO(I,J), J = 1,N)
      WRITE (51,105)
DO 27 I = 1,N          WRITE (51,120) (TAU(I,J), J = 1,N)
      WRITE (51,106)
DO 30 I = 1,NT          WRITE (51,120) (S(I,J), J = 1,NT)
      WRITE (51,107)
DO 35 I = 1,N          WRITE (51,120) (G(I,J), J = 1,N)
      WRITE (51,108)
DO 40 I = 1,N          WRITE (51,120) (V(I,J), J = 1,N)
      WRITE (51,109)
DO 45 I = 1,NT          WRITE (51,120) (F(I,J), J = 1,NT)
      RETURN
100 FORMAT (28H COORDINATES IN ATOMIC UNITS)
101 FORMAT (18H DIRECTION COSINES)
102 FORMAT (26H DISTANCES IN ATOMIC UNITS)
103 FORMAT (4H RHO)
104 FORMAT (4H TAU)
105 FORMAT (8H OVERLAP)
106 FORMAT (6H GAMMA)
107 FORMAT (2H V)
108 FORMAT (2H F)
120 FORMAT (1H ,10F11.6)

```

END

C SUBROUTINE INTER(N,NH,C,P,PA,F)
DIMENSION C(40,40), P(40,40), PA(18), F(40,40)
WRITE (51,100)
NT = (N-NH)*4+NH
DO 10 I = 1,NT
10 WRITE (51,120) (C(I,J), J = 1,NT)
WRITE (51,101)
DO 20 I = 1,NT
20 WRITE (51,120) (P(I,J), J = 1,NT)
WRITE (51,102)
WRITE (51,120) (PA(I), I = 1,N)
WRITE (51,103)
DO 30 I = 1,NT
30 WRITE (51,120) (F(I,J), J = 1,NT)
RETURN
100 FORMAT (2H C)
101 FORMAT (2H P)
102 FORMAT (3H PA)
103 FORMAT (2H F)
120 FORMAT (1H ,10F11.6)
END

C SUBROUTINE PREL(N,COORD,COS,RAD,ZS,RHO,TAU,NH)
DIMENSION COORD(3,18), COS(3,18,18), RAD(18,18)
12S(18), RHO(18,18), TAU(18,18)
DO 5 I = 1,3
DO 5 J = 1,N
5 COORD(I,J) = COORD(I,J)/•529167
DO 10 I = 1,N
DO 10 J = 1,N
RAD(I,J) = SQRT((COORD(1,J)-COORD(1,I))**2
1 + (COORD(2,J)-COORD(2,I))**2 + (COORD(3,J)-COORD(3,I))**2)
DO 10 K = 1,3
10 COS(K,I,J) = (COORD(K,J)-COORD(K,I))/RAD(I,J)

```

DO 30 I = 1,N
DO 30 J = 1,N
  KH(I,J) = U*D*(ZS(I)+ZS(J))*RAD(I,J)
  TAU(I,J) = (ZS(I)-ZS(J))/(ZS(I)+ZS(J))
  RETURN
END

```

```

C      SUBROUTINE OVERL(N,NH,ZS,COORD,COS,RAD,S,RHO,TAU)
C      DIMENSION ZS(18), COORD(3,18), COS(3,18,18), RAD(18,18), S(40,40),
C      1CA(3,3), CB(3,3), CC(3,3), RHO(18,18), TAU(18,18)
C      THIS ROUTINE CALCULATES THE OVERLAP MATRIX S, GIVEN
C      N, THE NUMBER OF ATOMS
C      NH, THE NUMBER OF HYDROGEN ATOMS
C      ZS, THE ARRAY OF SLATER EXPONENTS
C      COORD, THE MATRIX OF CARTESIAN COORDINATES, IN ATOMIC UNITS
C      COS, THE DIRECTION COSINE MATRIX
C      RAD, THE DISTANCE MATRIX, IN ATOMIC UNITS
C      RHO,
C      AND TAU.
C      THIS ROUTINE MAKES USE OF SUBROUTINES
C      SF(KEY,P,T) WHICH ALSO USES FUNCTION ADF
C      THE S MATRIX IS SET UP IN THE BASIS WHICH INCLUDES THE ROW TWO
C      ELEMENTS FIRST, THEN THE HYDROGEN ATOMS. EACH ROW TWO ELEMENT
C      IS ARRANGED SEPARATELY, WITH THE BASIS ARRANGED S, PX, PY, PZ FOR EACH.
C      NOT = N-NH
NOT1 = NOT+1
NS = 4*NOT
NS1 = NS+1
NT = NS+NH
DO 5 I = 1,NT
DO 5 J = 1,NT
  5 S(I,J) = U*U
  DO 6 I = 1,NT
    6 S(I,I) = 1.0
C      CALCULATE PERIOD 2 ATOM OVERLAP INTEGRALS

```

```

DO I U 1 = 1,NU1
I1 = I+1
DO I U J = 1,NU1
JSUB = 4*I-3
JSUB = 4*J-3
P = RHO(I,J)
T = TAU(I,J)
S(IJSUB,JJSUB) = SF(4,P,T)
TA = SF(5,P,T)
TB = SF(5,P,-T)
DO I L K = 1,NU1
JK = JSUB+K
S(IK,JJSUB) = TA*COS(K,I)
IK = ISUB+K
12 S(IK,JJSUB) = TD*COS(L,I)
DO I4 K = 1,3
DO I4 L = 1,3
CA(K,L) = 0.0
CB(K,L) = 0.0
14 CC(K,L) = 0.0
CB(1,1) = SF(6,P,T)
CB(2,2) = SF(7,P,T)
CB(3,3) = CB(2,2)
DEN = SQRT(F(COS(2,I,J)**2+COS(3,I,J)**2))
CA(1,1) = COS(1,I,J)
IF(DEN-.000001) 16,16,18
16 CA(Z,2) = 1.0
CA(3,3) = 1.0
GO TO 19
18 CA(1,2) = COS(2,I,J)
CA(1,3) = COS(3,I,J)
CA(2,2) = COS(3,I,J)/DEN
CA(2,3) = -COS(2,I,J)/DEN
CA(3,1) = -(CA(1,2)**2+CA(1,3)**2)/DEN
CA(3,2) = CA(1,1)*CA(1,2)/DEN

```

```

19 CA(3,3) = CA(1,1)*CA(1,3)/DEN
DO 15 K = 1,3
DO 15 L = 1,3
15 CC(K,L) = CA(K,L)
DO 17 K = 1,3
DO 17 L = 1,3
DO 17 M = 1,3
1K = ISUB+K
IL = JSUB+L
S(IK,IL) = 0.0
DO 17 M = 1,3
17 S(IK,IL) = S(IK,IL)+CA(M,K)*CB(M,M)*CC(M,L)
20 CONTINUE

C CALCULATE PERIOD 2 - HYDROGEN OVERLAP INTEGRALS
C
DO 40 I = 1,NOT
I1 = 4*I-3
I2 = I1+1
I3 = I2+1
I4 = I3+1
DO 40 J = NOT1,N
JSUB = 3*NOT+J
P = RHO(I,J)
T = TAU(I,J)
S(I1,JSUB) = SF(2,P,T)
SFS = SF(3,P,T)
S(I2,JSUB) = SFS*COS(1,I,J)
S(I3,JSUB) = SFS*COS(2,I,J)
S(I4,JSUB) = SFS*COS(3,I,J)
40
C CALCULATE HYDROGEN OVERLAP INTEGRALS
C
NB = 3*NOT
DO 60 I = NOT1,N
I1 = I+1
ISUB = NB+I

```

```

DO 60 J = I1,N
JSUB = NB+J
60 S(IJSUB,JJSUB) = SF(1,RHO(I,J),TAU(I,J))
DO 80 I = 1,NT
I1 = I+1
DO 80 J = I1,NT
80 S(J,I) = S(I,J)
RETURN
END

C
FUNCTION SF(KEY,P,T)
TS = ABSF(T)
IF(ABSF(T)-0.000001) 2,2,1
1 GO TO (10,20,30,40,50,60,70) KEY
2 GO TO (110,120,130,140,150,160,170) KEY
C 1S1S, 1S2S, 1S2PS, 2S2S, 2S2PS, 2PP2PP
10 SF = (P**3/4*0)*SQRTF((1.0-T*T)**3)*(ABF(1,2,P,TS)*ABF(2,0,P,TS) -
1 ABF(1,0,P,TS)*ABF(2,2,P,TS))*
RETURN
20 SF = (P**4/8*0)*SQRTF((1.0+T)**3*(1.0-T)**5/3*0)*(ABF(1,3,P,T)*
1 ABF(2,0,P,T) - ABF(1,2,P,T)*ABF(2,1,P,T) - ABF(1,1,P,T)*ABF(2,2,P,
2T) + ABF(1,0,P,T)*ABF(2,3,P,T))
RETURN
30 SF = (P**4*SQRTF((1.0+T)**3*(1.0-T)**5)/8*0)*(-ABF(1,3,P,T)*ABF(
1 2,1,P,T) + ABF(1,2,P,T)*ABF(2,0,P,T) + ABF(1,1,P,T)*ABF(2,3,P,T)
2 - ABF(1,0,P,T)*ABF(2,2,P,T))
RETURN
40 SF = (P**5*SQRTF((1.0-T*T)**5)/48.) * (ABF(1,4,P,TS)*ABF(2,0,P,TS)
1) - 2.0*ABF(1,2,P,TS)*ABF(2,2,P,TS) + ABF(1,0,P,TS)*ABF(2,4,P,TS))
RETURN
50 SF = (P**5*SQRTF((1.0-T*T)**5/3*0)/16*0)*
1(ABF(1,3,P,T)*(ABF(2,0,P,T)-ABF(2,2,P,T)) +
2ABF(1,1,P,T)*(ABF(2,4,P,T)-ABF(2,2,P,T)) +
3ABF(2,1,P,T)*(ABF(1,2,P,T)-ABF(1,4,P,T)) +
4ABF(2,3,P,T)*(ABF(1,2,P,T)-ABF(1,0,P,T)))
RETURN

```

```

60 SF = (P**5/16.0)*SQRRTF((1.0-T*T)**5) *
1(ABF(2,2,P,TS)*(ABF(1,0,P,TS) + ABF(1,4,P,TS)) -
2ABF(1,2,P,TS)*(ABF(2,0,P,TS) + ABF(2,4,P,TS)))
RETURN

70 SF = (P**5/32.0) * SQRRTF((1.0-T*T)**5) *
1(ABF(1,4,P,TS)*(ABF(2,0,P,TS)-ABF(2,2,P,TS)) +
2ABF(1,2,P,TS)*(ABF(2,4,P,TS)-ABF(2,0,P,TS)) +
3ABF(1,0,P,TS)*(ABF(2,2,P,TS)-ABF(2,4,P,TS)))
RETURN

110 SF = (P**3/6.0)*(3.0*ABF(1,2,P,T)-ABF(1,0,P,T))
RETURN

120 SF = (P**4/(12.0*SQRRTF(3.0))*(3.0*ABF(1,3,P,T)-ABF(1,1,P,T))
RETURN

130 SF = (P**4/12.0)*(3.0*ABF(1,2,P,T) ABF(1,0,P,T))
RETURN

140 SF = (P**5/360.0)*(15.0*ABF(1,4,P,T)-10.0*ABF(1,2,P,T)+3.0*ABF(1,0,
1,P,T))
RETURN

150 SF = (P**5/(60.0*SQRRTF(3.0))*(5.0*ABF(1,3,P,T)-ABF(1,1,P,T))
RETURN

160 SF = (P**5/120.0)*(5.0*ABF(1,4,P,T)-18.0*ABF(1,2,P,T) +
15.0*ABF(1,0,P,T))
RETURN

170 SF = (P**5/120.0)*(5.0*ABF(1,4,P,T)-6.0*ABF(1,2,P,T) +
1ABF(1,0,P,T))
RETURN
END

C
FUNCTION ABF(KAB,KP,P,T)
DIMENSION FACT(10), DUM(2)
EQUIVALENCE (DUM(2),FACT(1))
KP1 = KP+1
IF(IFBF-12345) 10,20,10
10 DUM(2) = 1.0
DO 12 I = 1,10
   F1 = I

```

```

12 FACT(I) = FACT(I-1)*FI
20 ABF = 0.0
      GO TO (30,130) KAB
30 DO 40 M = 1,KP1
      KM1 = KP-M+1
40 ABF = ABF+1.0/(P**M*FACT(KM1))
      AEF = ABF*FACT(KP)*EXP(-P)
      RETURN
130 BA = 0.0
      BB = 0.0
      PT = P*T
      DO 140 M = 1,KP1
      KM = KP-M
      KM1 = KP-M+1
      ABF = 1.0/((P*T)**M*FACT(KM1))
      BA = BA+ABF
      BB = BB+(-1.0)**KM*ABF
140 EPT = EXP(-PT)
      ABF = -EPT*FACT(KP)*BA-FACT(KP)*BB/EPT
      RETURN
END

```

C

```

SUBROUTINE GVAB(N,NH,ZS,RAD,G,V,RHO,TAU,Z,IPT)
DIMENSION ZS(18), RAD(18,18), G(18,18), V(18,18), RHO(18,18),
1 TAU(18,18), IPT(5), Z(18)
NOT = N-NH
NOT1 = NOT+1
DO 10 I = 1,N
DO 10 J = 1,N
      G(I,J) = 0.0
10 V(I,J) = 0.0
DO 20 I = 1,NOT
      I1 = I+1
20 DO J = 1,NOT
      G(I,J) = GF(3,RHO(I,J),TAU(I,J),RAD(I,J))

```

```

G(J,I) = G(I,J)
RD = RAD(I,J)
P = ZS(I)*RD
V(I,J) = VF(2,P,RD)*Z(J)
P = ZS(J)*RD
20 V(J,I) = VF(2,P,RD) *Z(I)
DO 40 I = 1,NOT1,N
DO 40 J = NOT1,N
RD = RAD(I,J)
G(I,J) = GF(2,RHO(I,J),-TAU(I,J),RD)
G(J,I) = G(I,J)
P = ZS(I)*RD
V(I,J) = VF(2,P,RD)*Z(J)
P = ZS(J)*RD
40 V(J,I) = VF(1,P,RD)*Z(I)
DO 60 I = NOT1,N
I1 = I+1
DO 60 J = I1,N
G(I,J) = GF(1,RHO(I,J),TAU(I,J),RAD(I,J))
G(J,I) = G(I,J)
RD = RAD(I,J)
P = ZS(I)*RD
V(I,J) = VF(1,P,RD)*Z(J)
P = ZS(J)*RD
60 V(J,I) = VF(1,P,RD)*Z(I)
DO 80 I = 1,NOT1,N
80 G(I,I) = 0.36328125*ZS(I)
DO 81 I = NOT1,N
81 G(I,I) = 0.625*ZS(I)
IF(IPT(4)-2) 90,85,90
85 DO 87 I = 1,N
DO 87 J = 1,N
87 V(I,J) = Z(J)*G(I,J)
DO 88 I = 1,N
88 V(I,I) = 0.0
90 RETURN

```

END

C

```
FUNCTION GF(KEY,P,T,R)
IF(ABSF(T)-0.000001) 1,1,2
1  GO TO (110,120,130) KEY
2  AK = 0.5*(T+1.0/T)
PA = (1.0+T)*P
PB = (1.0-T)*P
GO TO (10,20,30) KEY
10 GF = (1.0-(1.0-AK)**2*((2.0+AK)/4. PA/4.0)*EXP(-2.0*PA) -
1 (1.0+AK)**2*((2.0-AK)/4.0+PB/4.0)*EXP(-2.0*PB))/R
GO TO 100
20 GF = (1.0-(1.0-AK)**3*((1.0-5.0*AK 4.0*AK**2)/16.0-AK*PA/8.0)-
1 EXP(-2.0*PA) - (1.0+AK)**2*((15.0 22.0*AK+15.0*AK**2-4.0*AK**3)-
2/16.0+3.0*(3.0-3.0*AK+AK**2)*PB/8. (2.0-AK)*PB**2/4.0+PB**3/12.0)*
3EXP(-2.0*PB))/R
GO TO 100
30 GF = (1.0-(1.0-AK)**3*((8.-AK-27.0*AK**2-30.0*AK**3-10.0*AK**4)-
1 16.0+(11.0-19.0*AK-44.0*AK**2-20. *AK**3)*PA/32.0+(1.0-5.0*AK
2 -4.0*AK**2)*PA**2/16.0-AK*PA**3/24.0)*EXP(-2.0*PA) - (1.0+AK)**3
3*((8.+AK-27.0*AK**2+30.0*AK**3-10. *AK**4)/16.0+(11.0+19.0*AK-44.0
4*AK**2+20.0*AK**3)*PB/32.0+(1.0+5. *AK-4.0*AK**2)*PB**2/16.0
5+AK*PB**3/24.)*EXP(-2.0*PB))/R
GO TO 100
110 GF = (1.0-(1.0+11.0*P/8.0+3.0*P**2/4.0+P**3/6.0)*EXP(-2.0*P))/R
GO TO 100
120 GF = (1.0-(1.0+25.0*P/16.0+9.0*P**2/8.0+23.0*P**3/48.0+P**4/8.0
1+P**5/60.0)*EXP(-2.0*P))/R
GO TO 100
130 GF = (1.0-(1.0+419.0*P/256.0+163.0*P**2/128.0+119.0*P**3/192.0
1+5.*P**4/24.0+P**5/20.0+P**6/120.)*EXP(-2.0*P))/R
100 RETURN
END
```

C

```
FUNCTION VF(KEY,P,R)
GO TO (10,20) KEY
```

```

10 VF = (1.0-(1.0+P) *EXP(-(2.0*P)) /R
GO TO 100
20 VF = (1.0-(1.0+1.5*P+P**2+P**3/3.0)*EXP(-(2.0*P)) /R
100 RETURN
END

```

```

C
SUBROUTINE HDIAG(H,U,IEGEN,N,NR)
DIMENSION H(40,40), ROOT(40), U(40,40), B(40,5)
IC = 0
DO 10 J = 1,N
DO 10 I = 1,J
IC = IC+1
10 H(IC) = H(I,J)
CALL GIVENS(N,N,H,B,ROOT,U)
IC = 0
DO 30 I = 1,N
DO 30 J = 1,N
IC = IC+1
30 H(J,I) = U(IC)
DO 40 I = 1,N
DO 40 J = 1,N
U(I,J) = H(J,I)
40 H(J,I) = 0.0
DO 50 I = 1,N
50 H(I,I) = ROOT(I)
RETURN
END
SUBROUTINE GIVENS (NX,NROOTX,A,B,ROOT,VECT)
0003
C EIGENVALUES AND EIGENVECTORS BY GIVENS METHOD.
- - - - -
4
5
6
7
8
9
0009
0000
0010
C CALCULATES EIGENVALUES AND EIGENVECTORS OF REAL SYMMETRIC MATRIX
C BY THE MODIFIED GIVENS METHOD. THE PARAMETERS ARE•••
C NX ORDER OF MATRIX

```

C NROOTX NUMBER OF ROOTS WANTED. MOST NEGATIVE ROOTS ARE
 C FOUND FIRST. IF NO VECTORS ARE WANTED, MAKE THIS
 C NUMBER NEGATIVE.
 A MATRIX STORED BY COLUMNS IN PACKED UPPER TRIANGULAR
 FORM, I.E. OCCUPYING $NX*(NX+1)/2$ CONSECUTIVE
 LOCATIONS.
 ROOT ARRAY TO HOLD THE EIGENVALUES. MUST BE AT LEAST
 C NROOTX CELLS LONG.
 VECT EIGENVECTOR ARRAY. EACH COLUMN WILL HOLD AN
 C EIGENVECTOR FOR THE CORRESPONDING ROOT. MUST BE
 C AT LEAST $NX*NROOTX$ CELLS LONG, UNLESS NO VECTORS
 C ARE REQUESTED (NEGATIVE NROOTX). IN THIS LATTER
 C CASE, THE ARGUMENT VECT IS JUST A DUMMY, AND THE
 C STORAGE IS NOT USED.
 THE ARRAYS A AND B ARE DESTROYED BY THE COMPUTATION. THE RESULTS
 C APPEAR IN ROOT AND VECT.
 THE ORIGINAL REFERENCE TO THE GIVENS TECHNIQUE IS IN OAK RIDGE
 C REPORT NUMBER ORNL 1574 (PHYSICS), BY WALLACE GIVENS.
 THE METHOD AS PRESENTED IN THIS PROGRAM CONSISTS OF FOUR STEPS,
 C ALL MODIFICATIONS OF THE ORIGINAL METHOD. . . .
 FIRST, THE INPUT MATRIX IS REDUCED TO TRIDIAGONAL FORM BY THE
 HOUSEHOLDER TECHNIQUE (J. H. WILKINSON, COMP. J. 3, 23 (1960)).
 THE ROOTS ARE THEN LOCATED BY THE STURM SEQUENCE METHOD (J. M.
 ORTEGA, J. ACM 7, 260 (1960)). THE VECTORS OF THE TRIDIAGONAL
 FORM ARE THEN EVALUATED (J. H. WILKINSON, COMP. J. 1, 90 (1958)),
 AND LAST THE TRIDIAGONAL VECTORS ARE ROTATED TO VECTORS OF THE
 C ORIGINAL ARRAY (FIRST REFERENCE).
 VECTORS FOR DEGENERATE (OR NEAR-DEGENERATE) ROOTS ARE FORCED
 C TO BE ORTHOGONAL, USING A METHOD SUGGESTED BY B. GARBOW, ARGONNE
 NATIONAL LABS (PRIVATE COMMUNICATION, 1964). THE GRAM-SCHMIDT
 PROCESS IS USED FOR THE ORTHOGONALIZATION.
 40
 0041
 0042
 0043
 0044
 45

```

0047
0048
0049
0050
0051
0052
0053
0054
0055
0056
0057
0058
0059
0060
0061
0062
0063
0064
0065
0066
0067
0068
0069
0070
0071
0072
0073
0074
0075
0076
0077
0078
0079
0080
0081

DIMENSION B(NX,5), A(1), ROOT(1), VECT(NX,NROOTX)
DATA (KILLBIT = 77777777777776B), (ETA = 1.0E-10)

N = NX
NROOT = XABSF(NROOTX)
GO TO (1010,105) N
ROOT = A
GO TO 807
CONTINUE

C      NSIZE   NUMBER OF ELEMENTS IN THE ARRAY
C      NSIZE = N*(N+1)/2
NM1 = N - 1
NM2 = N - 2

C      TRIIDIAGONALIZATION OF SYMMETRIC MATRIX
C      - - - - -
ID = 0
IA = 1

DO 200 J=1,NM2
      COUNTS ROWS OF A-MATRIX TO BE DIAGONALIZED
      START OF NON-CODIAGONAL ELEMENTS IN THE ROW
      POSITION OF DIAGONAL ELEMENT ON ROW BEING CODIAGONALIZED
      IA = IA+J+2
      ID = ID + J
      JUMP = J+1

DO 200 J=1,NM2
      COUNTS ROWS OF A-MATRIX TO BE DIAGONALIZED
      START OF NON-CODIAGONAL ELEMENTS IN THE ROW
      POSITION OF DIAGONAL ELEMENT ON ROW BEING CODIAGONALIZED
      IA = IA+J+2
      ID = ID + J
      JUMP = J+1

      SUM SQUARES OF NON-CODIAGONAL ELEMENTS IN ROW J
      SUM = 0.0
      DO 100 I=IA,NSIZE, JUMP
      SUM = SUM + A(I)**2
      JUMP = JUMP + 1
      TEMP = A(ID+J)
      IF(SUM) 110,120,110
      100

```

```

C      NO TRANSFORMATION NECESSARY IF ALL THE NON-CODIAGONAL
C      ELEMENTS ARE ZERO.
120      B(J) = TEMP
          A(ID+J) = 0.0
          GO TO 200
          89

C      NOW COMPLETE THE SUM OF OFF-DIAGONAL SQUARES
110      SUM = SQRFF(SUM+ TEMP**2)
          90
          91

C      NEW CODIAGONAL ELEMENT
          B(J) = -SIGNF(SUM,TEMP)
          92
          93

C      FIRST NON-ZERO ELEMENT OF THIS W-VECTOR
          JUMP = J + 1
          B(JUMP,2) = SQRFF((1.0 + ABSF(TEMP)/SUM)/2.0)
          94
          95

C      FORM REST OF THE W-VECTOR ELEMENTS
          TEMP = SIGNF(0.5/(B(JUMP,2)*SUM),TEMP)
DO 130  I=IA,NSIZE,JUMP
          JUMP = JUMP + 1
          B(JUMP,2) = A(I)*TEMP
          96
          97
          98
          99

C      FORM P-VECTOR AND SCALAR. P-VECTOR = A-MATRIX*V-VECTOR.
          SCALAR = W-VECTOR*P-VECTOR.
          100
          101
          102
          103
          104
          105
          106
          107
          108
          109
          110
          111
          112
          113
          114
          115
          116
          117
          118

```

```

C           RUNS OVER THE NON-ZERO P-ELEMENTS          0119
C           RUNS OVER ELEMENTS OF W-VECTOR            0120
TEMP = TEMP + B(II,2)*A(JJ)                         0121
                                                0122
C           CHANGE INCREMENTING MODE AT THE DIAGONAL ELEMENTS 0123
IF(II-1) 210,140,140
JJ = JJ + II                                         0125
GO TO 180                                           0126
JJ = JJ + 1                                         0127
CONTINUE                                           0128
                                                0129
C           BUILD UP THE K-SCALAR (AK)
AK = AK + TEMP*B(I,2)                             0130
B(I) = TEMP                                         0131
MOVE IC TO TOP OF NEXT A-MATRIX -ROW-             0132
IC = IC + 1                                         0133
                                                0134
                                                0135
C           FORM THE Q-VECTOR
DO 150 I=J1,N                                     0136
B(I) = B(I) - AK*B(I,2)                           0137
                                                0138
                                                0139
C           TRANSFORM THE REST OF THE A-MATRIX
JJ = ID + J                                         0140
MOVE W-VECTOR INTO THE OLD A-MATRIX LOCATIONS TO SAVE SPACE 0141
I           RUNS OVER THE SIGNIFICANT ELEMENTS OF THE W-VECTOR 0142
DO 160 I=J1,N                                     0143
A(JJ) = B(I,2)                                     0144
                                                0145
                                                0146
                                                0147
DO 170 II=J1,I                                     0148
JJ = JJ + 1                                         0149
A(JJ) = A(JJ) - 2.0*(B(I)*B(II,2))      B(I,2)*B(II) 0150
JJ = JJ + J                                         0151
CONTINUE                                           0152
                                                0153
C           MOVE LAST CODIAGONAL ELEMENT OUT INTO ITS PROPER PLACE 0154

```

```

0155      B(N-1) = A(NSIZE-1)
0156      A(NSIZE -1) = 0.0
0157      157
0158      SHIFT ALL CODIAGONAL ELEMENTS DOWN ONE PLACE TO TAKE ADVANTAGE
0159      OF FORWARD INDEXING (I.E. FIRST CODIAGONAL ELEMENT MUST BE ZERO).
0160      DO 205 J=1,NM1
0161      B(N+1-J) = B(N-J)
0162      B(1) = 0.
0163      163
0164      STURM SEQUENCE ITERATION TO OBTAIN ROOTS OF TRIDIAGONAL FORM
0165      - - - - -
0166      166
0167      167
0168      MOVE DIAGONAL ELEMENTS INTO SECOND N ELEMENTS OF B-VECTOR.
0169      THIS IS A MORE CONVENIENT INDEXING POSITION.
0170      ALSO, PUT SQUARE OF CODIAGONAL ELEMENTS IN THIRD N ELEMENTS
0171      OF B-VECTOR FOR USE IN STURM SEQUENCE EVALUATION.
0172      AT THE SAME TIME, COMPUTE THE NORM OF THE MATRIX.
0173      173
0174      ANORM = 0.
0175      JUMP = 1
0176      DO 300 J=1,N
0177      B(J,3) = B(J)**2
0178      B(J,2) = A(JUMP)
0179      ANCRA = ANORM + 2.0*B(J,3) + A(JUMP)**2
0180      0180
0181      JUMP = JUMP + J + 1
0182      182
0183      NORM OF MATRIX AND SMALL CONVERGENCE LIMIT.
0184      ANORM = SQRTF(ANORM)
0185      DELTA = ANORM*ETA
0186      IF (DELTA) 320,1001
0187      ROOT(I) HOLDS LOWER LIMIT OF EIGENVALUE I.
0188      B(I,4) HOLDS UPPER LIMIT OF EIGENVALUE I.
0189      189
0190      DO 310 I=1,NROOT

```

```

      ROOT(I) = -ANORM          0191
      B(I,4) = +ANORM          0192
      C           ISOLATE THE ROOTS. 0193
      DO 330   I=1,NROOT        0194
      IMPROVE THE TRIAL ROOT    0195
      TRIAL = (ROOT(I)+B(I,4))*0.5 0196
      IF((B(I,4)-ROOT(I))-DELTA) 330,330,350 198

      C           FORM STURM SEQUENCE. 0199
      C           NOMATCH IS ONE GREATER THAN THE NUMBER OF ROOTS LESS THAN 0200
      C           THE TRIAL VALUE. 0201
      NOMATCH = 1                0202
      F1 = 1.0                  0203
      DO 360   J=1,N            0204
      DIAG = B(J,2) - TRIAL    0205
      GO TO 400                 0206

      IF (B(J)) 410,420        0207
      F0 = DIAG*SIGNF(1.0,F1)  0208
      GO TO 400                 0209
      F0 = 0                     210
      IF (B(J-1)) 430,440        0211
      F0 = F0 - B(J,3)*SIGNF(1.0,F2) 0212
      GO TO 400                 0213
      F0 = DIAG*F1              0214
      IF (F0) 450,460,470        0215
      F0 = SIGNF(0.0,F1)       0216
      GO TO 510                 0217
      F0 = F0 - B(J,3)*F2       0218
      IF (F0) 520,520,510        0219
      F0 = SIGNF(0.0,F1)       0220
      GO TO 510                 0221
      F0 = F0 *SIGNF(1.0,F1)    0223
      IF (F1) 520,480,510        0224
      F0 = SIGNF(0.0,F1)       0225
      NOMATCH = NOMATCH + 1     0226

```

```

      F2 = F1          227
      F1 = F0          228
      CONTINUE         229
                           0229
                           0230
                           0231
                           0232
                           0233
                           231
                           232
                           0233
                           235
                           0236
                           0237
                           0238
                           0239
                           239
                           0240
                           240
                           0243
                           244
                           0245
                           246
                           247
                           0248
                           248
                           249
                           250
                           0251
                           0252
                           0253
                           253
                           254
                           0255
                           255
                           0256
                           0257
                           0258
                           0259
                           0260
                           0261
                           261
                           262
                           0262
                           263
                           0263
                           264
                           0264
                           265
                           0265
                           266
                           0266
                           267
                           0267
                           268
                           0268
                           269
                           0269
                           270
                           0270
                           271
                           0271
                           272
                           0272
                           273
                           0273
                           274
                           0274
                           275
                           0275
                           276
                           0276
                           277
                           0277
                           278
                           0278
                           279
                           0279
                           280
                           0280
                           281
                           0281
                           282
                           0282
                           283
                           0283
                           284
                           0284
                           285
                           0285
                           286
                           0286
                           287
                           0287
                           288
                           0288
                           289
                           0289
                           290
                           0290
                           291
                           0291
                           292
                           0292
                           293
                           0293
                           294
                           0294
                           295
                           0295
                           296
                           0296
                           297
                           0297
                           298
                           0298
                           299
                           0299
                           300
                           0300
                           301
                           0301
                           302
                           0302
                           303
                           0303
                           304
                           0304
                           305
                           0305
                           306
                           0306
                           307
                           0307
                           308
                           0308
                           309
                           0309
                           310
                           0310
                           311
                           0311
                           312
                           0312
                           313
                           0313
                           314
                           0314
                           315
                           0315
                           316
                           0316
                           317
                           0317
                           318
                           0318
                           319
                           0319
                           320
                           0320
                           321
                           0321
                           322
                           0322
                           323
                           0323
                           324
                           0324
                           325
                           0325
                           326
                           0326
                           327
                           0327
                           328
                           0328
                           329
                           0329
                           330
                           0330
                           331
                           0331
                           332
                           0332
                           333
                           0333
                           334
                           0334
                           335
                           0335
                           336
                           0336
                           337
                           0337
                           338
                           0338
                           339
                           0339
                           340
                           0340
                           341
                           0341
                           342
                           0342
                           343
                           0343
                           344
                           0344
                           345
                           0345
                           346
                           0346
                           347
                           0347
                           348
                           0348
                           349
                           0349
                           350
                           0350
                           351
                           0351
                           352
                           0352
                           353
                           0353
                           354
                           0354
                           355
                           0355
                           356
                           0356
                           357
                           0357
                           358
                           0358
                           359
                           0359
                           360
                           0360
                           361
                           0361
                           362
                           0362
                           363
                           0363
                           364
                           0364
                           365
                           0365
                           366
                           0366
                           367
                           0367
                           368
                           0368
                           369
                           0369
                           370
                           0370
                           371
                           0371
                           372
                           0372
                           373
                           0373
                           374
                           0374
                           375
                           0375
                           376
                           0376
                           377
                           0377
                           378
                           0378
                           379
                           0379
                           380
                           0380
                           381
                           0381
                           382
                           0382
                           383
                           0383
                           384
                           0384
                           385
                           0385
                           386
                           0386
                           387
                           0387
                           388
                           0388
                           389
                           0389
                           390
                           0390
                           391
                           0391
                           392
                           0392
                           393
                           0393
                           394
                           0394
                           395
                           0395
                           396
                           0396
                           397
                           0397
                           398
                           0398
                           399
                           0399
                           400
                           0400
                           401
                           0401
                           402
                           0402
                           403
                           0403
                           404
                           0404
                           405
                           0405
                           406
                           0406
                           407
                           0407
                           408
                           0408
                           409
                           0409
                           410
                           0410
                           411
                           0411
                           412
                           0412
                           413
                           0413
                           414
                           0414
                           415
                           0415
                           416
                           0416
                           417
                           0417
                           418
                           0418
                           419
                           0419
                           420
                           0420
                           421
                           0421
                           422
                           0422
                           423
                           0423
                           424
                           0424
                           425
                           0425
                           426
                           0426
                           427
                           0427
                           428
                           0428
                           429
                           0429
                           430
                           0430
                           431
                           0431
                           432
                           0432
                           433
                           0433
                           434
                           0434
                           435
                           0435
                           436
                           0436
                           437
                           0437
                           438
                           0438
                           439
                           0439
                           440
                           0440
                           441
                           0441
                           442
                           0442
                           443
                           0443
                           444
                           0444
                           445
                           0445
                           446
                           0446
                           447
                           0447
                           448
                           0448
                           449
                           0449
                           450
                           0450
                           451
                           0451
                           452
                           0452
                           453
                           0453
                           454
                           0454
                           455
                           0455
                           456
                           0456
                           457
                           0457
                           458
                           0458
                           459
                           0459
                           460
                           0460
                           461
                           0461
                           462
                           0462
                           463
                           0463
                           464
                           0464
                           465
                           0465
                           466
                           0466
                           467
                           0467
                           468
                           0468
                           469
                           0469
                           470
                           0470
                           471
                           0471
                           472
                           0472
                           473
                           0473
                           474
                           0474
                           475
                           0475
                           476
                           0476
                           477
                           0477
                           478
                           0478
                           479
                           0479
                           480
                           0480
                           481
                           0481
                           482
                           0482
                           483
                           0483
                           484
                           0484
                           485
                           0485
                           486
                           0486
                           487
                           0487
                           488
                           0488
                           489
                           0489
                           490
                           0490
                           491
                           0491
                           492
                           0492
                           493
                           0493
                           494
                           0494
                           495
                           0495
                           496
                           0496
                           497
                           0497
                           498
                           0498
                           499
                           0499
                           500
                           0500
                           501
                           0501
                           502
                           0502
                           503
                           0503
                           504
                           0504
                           505
                           0505
                           506
                           0506
                           507
                           0507
                           508
                           0508
                           509
                           0509
                           510
                           0510
                           511
                           0511
                           512
                           0512
                           513
                           0513
                           514
                           0514
                           515
                           0515
                           516
                           0516
                           517
                           0517
                           518
                           0518
                           519
                           0519
                           520
                           0520
                           521
                           0521
                           522
                           0522
                           523
                           0523
                           524
                           0524
                           525
                           0525
                           526
                           0526
                           527
                           0527
                           528
                           0528
                           529
                           0529
                           530
                           0530
                           531
                           0531
                           532
                           0532
                           533
                           0533
                           534
                           0534
                           535
                           0535
                           536
                           0536
                           537
                           0537
                           538
                           0538
                           539
                           0539
                           540
                           0540
                           541
                           0541
                           542
                           0542
                           543
                           0543
                           544
                           0544
                           545
                           0545
                           546
                           0546
                           547
                           0547
                           548
                           0548
                           549
                           0549
                           550
                           0550
                           551
                           0551
                           552
                           0552
                           553
                           0553
                           554
                           0554
                           555
                           0555
                           556
                           0556
                           557
                           0557
                           558
                           0558
                           559
                           0559
                           560
                           0560
                           561
                           0561
                           562
                           0562
                           563
                           0563
                           564
                           0564
                           565
                           0565
                           566
                           0566
                           567
                           0567
                           568
                           0568
                           569
                           0569
                           570
                           0570
                           571
                           0571
                           572
                           0572
                           573
                           0573
                           574
                           0574
                           575
                           0575
                           576
                           0576
                           577
                           0577
                           578
                           0578
                           579
                           0579
                           580
                           0580
                           581
                           0581
                           582
                           0582
                           583
                           0583
                           584
                           0584
                           585
                           0585
                           586
                           0586
                           587
                           0587
                           588
                           0588
                           589
                           0589
                           590
                           0590
                           591
                           0591
                           592
                           0592
                           593
                           0593
                           594
                           0594
                           595
                           0595
                           596
                           0596
                           597
                           0597
                           598
                           0598
                           599
                           0599
                           600
                           0600
                           601
                           0601
                           602
                           0602
                           603
                           0603
                           604
                           0604
                           605
                           0605
                           606
                           0606
                           607
                           0607
                           608
                           0608
                           609
                           0609
                           610
                           0610
                           611
                           0611
                           612
                           0612
                           613
                           0613
                           614
                           0614
                           615
                           0615
                           616
                           0616
                           617
                           0617
                           618
                           0618
                           619
                           0619
                           620
                           0620
                           621
                           0621
                           622
                           0622
                           623
                           0623
                           624
                           0624
                           625
                           0625
                           626
                           0626
                           627
                           0627
                           628
                           0628
                           629
                           0629
                           630
                           0630
                           631
                           0631
                           632
                           0632
                           633
                           0633
                           634
                           0634
                           635
                           0635
                           636
                           0636
                           637
                           0637
                           638
                           0638
                           639
                           0639
                           640
                           0640
                           641
                           0641
                           642
                           0642
                           643
                           0643
                           644
                           0644
                           645
                           0645
                           646
                           0646
                           647
                           0647
                           648
                           0648
                           649
                           0649
                           650
                           0650
                           651
                           0651
                           652
                           0652
                           653
                           0653
                           654
                           0654
                           655
                           0655
                           656
                           0656
                           657
                           0657
                           658
                           0658
                           659
                           0659
                           660
                           0660
                           661
                           0661
                           662
                           0662
                           663
                           0663
                           664
                           0664
                           665
                           0665
                           666
                           0666
                           667
                           0667
                           668
                           0668
                           669
                           0669
                           670
                           0670
                           671
                           0671
                           672
                           0672
                           673
                           0673
                           674
                           0674
                           675
                           0675
                           676
                           0676
                           677
                           0677
                           678
                           0678
                           679
                           0679
                           680
                           0680
                           681
                           0681
                           682
                           0682
                           683
                           0683
                           684
                           0684
                           685
                           0685
                           686
                           0686
                           687
                           0687
                           688
                           0688
                           689
                           0689
                           690
                           0690
                           691
                           0691
                           692
                           0692
                           693
                           0693
                           694
                           0694
                           695
                           0695
                           696
                           0696
                           697
                           0697
                           698
                           0698
                           699
                           0699
                           700
                           0700
                           701
                           0701
                           702
                           0702
                           703
                           0703
                           704
                           0704
                           705
                           0705
                           706
                           0706
                           707
                           0707
                           708
                           0708
                           709
                           0709
                           710
                           0710
                           711
                           0711
                           712
                           0712
                           713
                           0713
                           714
                           0714
                           715
                           0715
                           716
                           0716
                           717
                           0717
                           718
                           0718
                           719
                           0719
                           720
                           0720
                           721
                           0721
                           722
                           0722
                           723
                           0723
                           724
                           0724
                           725
                           0725
                           726
                           0726
                           727
                           0727
                           728
                           0728
                           729
                           0729
                           730
                           0730
                           731
                           0731
                           732
                           0732
                           733
                           0733
                           734
                           0734
                           735
                           0735
                           736
                           0736
                           737
                           0737
                           738
                           0738
                           739
                           0739
                           740
                           0740
                           741
                           0741
                           742
                           0742
                           743
                           0743
                           744
                           0744
                           745
                           0745
                           746
                           0746
                           747
                           0747
                           748
                           0748
                           749
                           0749
                           750
                           0750
                           751
                           0751
                           752
                           0752
                           753
                           0753
                           754
                           0754
                           755
                           0755
                           756
                           0756
                           757
                           0757
                           758
                           0758
                           759
                           0759
                           760
                           0760
                           761
                           0761
                           762
                           0762
                           763
                           0763
                           764
                           0764
                           765
                           0765
                           766
                           0766
                           767
                           0767
                           768
                           0768
                           769
                           0769
                           770
                           0770
                           771
                           0771
                           772
                           0772
                           773
                           0773
                           774
                           0774
                           775
                           0775
                           776
                           0776
                           777
                           0777
                           778
                           0778
                           779
                           0779
                           780
                           0780
                           781
                           0781
                           782
                           0782
                           783
                           0783
                           784
                           0784
                           785
                           0785
                           786
                           0786
                           787
                           0787
                           788
                           0788
                           789
                           0789
                           790
                           0790
                           791
                           0791
                           792
                           0792
                           793
                           0793
                           794
                           0794
                           795
                           0795
                           796
                           0796
                           797
                           0797
                           798
                           0798
                           799
                           0799
                           800
                           0800
                           801
                           0801
                           802
                           0802
                           803
                           0803
                           804
                           0804
                           805
                           0805
                           806
                           0806
                           807
                           0807
                           808
                           0808
                           809
                           0809
                           810
                           0810
                           811
                           0811
                           812
                           0812
                           813
                           0813
                           814
                           0814
                           815
                           0815
                           816
                           0816
                           817
                           0817
                           818
                           0818
                           819
                           0819
                           820
                           0820
                           821
                           0821
                           822
                           0822
                           823
                           0823
                           824
                           0824
                           825
                           0825
                           826
                           0826
                           827
                           0827
                           828
                           0828
                           829
                           0829
                           830
                           0830
                           831
                           0831
                           832
                           0832
                           833
                           0833
                           834
                           0834
                           835
                           0835
                           836
                           0836
                           837
                           0837
                           838
                           0838
                           839
                           0839
                           840
                           0840
                           841
                           0841
                           842
                           0842
                           843
                           0843
                           844
                           0844
                           845
                           0845
                           846
                           0846
                           847
                           0847
                           848
                           0848
                           849
                           0849
                           850
                           0850
                           851
                           0851
                           852
                           0852
                           853
                           0853
                           854
                           0854
                           855
                           0855
                           856
                           0856
                           857
                           0857
                           858
                           0858
                           859
                           0859
                           860
                           0860
                           861
                           0861
                           862
                           0862
                           863
                           0863
                           864
                           0864
                           865
                           0865
                           866
                           0866
                           867
                           0867
                           868
                           0868
                           869
                           0869
                           870
                           0870
                           871
                           0871
                           872
                           0872
                           873
                           0873
                           874
                           0874
                           875
                           0875
                           876
                           0876
                           877
                           0877
                           878
                           0878
                           879
                           0879
                           880
                           0880
                           881
                           0881
                           882
                           0882
                           883
                           0883
                           884
                           0884
                           885
                           0885
                           886
                           0886
                           887
                           0887
                           888
                           0888
                           889
                           0889
                           890
                           0890
                           891
                           0891
                           892
                           0892
                           893
                           0893
                           894
                           0894
                           895
                           0895
                           896
                           0896
                           897
                           0897
                           898
                           0898
                           899
                           0899
                           900
                           0900
                           901
                           0901
                           902
                           0902
                           903
                           0903
                           904
                           0904
                           905
                           0905
                           906
                           0906
                           907
                           0907
                           908
                           0908
                           909
                           0909
                           910
                           0910
                           911
                           0911
                           912
                           0912
                           913
                           0913
                           914
                           0914
                           915
                           0915
                           916
                           0916
                           917
                           0917
                           918
                           0918
                           919
                           0919
                           920
                           0920
                           921
                           0921
                           922
                           0922
                           923
                           0923
                           924
                           0924
                           925
                           0925
                           926
                           0926
                           927
                           0927
                           928
                           0928
                           929
                           0929
                           930
                           0930
                           931
                           0931
                           932
                           0932
                           933
                           0933
                           934
                           0934
                           935
                           0935
                           936
                           0936
                           937
                           0937
                           938
                           0938
                           939
                           0939
                           940
                           0940
                           941
                           0941
                           942
                           0942
                           943
                           0943
                           944
                           0944
                           945
                           0945
                           946
                           0946
                           947
                           0947
                           948
                           0948
                           949
                           0949
                           950
                           0950
                           951
                           0951
                           952
                           0952
                           953
                           0953
                           954
                           0954
                           955
                           0955
                           956
                           0956
                           957
                           0957
                           958
                           0958
                           959
                           0959
                           960
                           0960
                           961
                           0961
                           962
                           0962
                           963
                           0963
                           964
                           0964
                           965
                           0965
                           966
                           0966
                           967
                           0967
                           968
                           0968
                           969
                           0969
                           970
                           0970
                           971
                           0971
                           972
                           0972
                           973
                           0973
                           974
                           0974
                           975
                           0975
                           976
                           0976
                           977
                           0977
                           978
                           0978
                           979
                           0979
                           980
                           0980
                           981
                           0981
                           982
                           0982
                           983
                           0983
                           984
                           0984
                           985
                           0985
                           986
                           0986
                           987
                           0987
                           988
                           0988
                           989
                           0989
                           990
                           0990
                           991
                           0991
                           992
                           0992
                           993
                           0993
                           994
                           0994
                           995
                           0995
                           996
                           0996
                           997
                           0997
                           998
                           0998
                           999
                           0999
                           1000
                           0100
                           1001
                           0101
                           1002
                           0102
                           1003
                           0103
                           1004
                           0104
                           1005
                           0105
                           1006
                           0106
                           1007
                           0107
                           1008
                           0108
                           1009
                           0109
                           1010
                           0110
                           1011
                           0111
                           1012
                           0112
                           1013
                           0113
                           1014
                           0114
                           1015
                           0115
                           1016
                           0116
                           1017
                           0117
                           1018
                           0118
                           1019
                           0119
                           1020
                           0120
                           1021
                           0121
                           1022
                           0122
                           1023
                           0123
                           1024
                           0124
                           1025
                           0125
                           1026
                           0126
                           1027
                           0127
                           1028
                           0128
                           1029
                           0129
                           1030
                           0130
                           1031
                           0131
                           1032
                           0132
                           1033
                           0133
                           1034
                           0134
                           1035
                           0135
                           1036
                           0136
                           1037
                           0137
                           1038
                           0138
                           1039
                           0139
                           1040
                           0140
                           1041
                           0141
                           1042
                           0142
                           1043
                           0143
                           1044
                           0144
                           1045
                           0145
                           1046
                           0146
                           1047
                           0147
                           1048
                           0148
                           1049
                           0149
                           1050
                           0150
                           1051
                           0151
                           1052
                           0152
                           1053
                           0153
                           1054
                           0154
                           1055
                           0155
                           1056
                           0156
                           1057
                           0157
                           1058
                           0158
                           1059
                           0159
                           1060
                           0160
                           1061
                           0161
                           1062
                           0162
                           1063
                           0163
                           1064
                           0164
                           1065
                           0165
                           1066
                           0166
                           1067
                           0167
                           1068
                           0168
                           1069
                           0169
                           1070
                           0170
                           1071
                           0171
                           1072
                           0172
                           1073
                           0173
                           1074
                           0174
                           1075
                           0175
                           1076
                           0176
                           1077
                           0177
                           1078
                           0178
                           1079
                           0179
                           1080
                           0180
                           1081
                           0181
                           1082
                           0182
                           1083
                           0183
                           1084
                           0184
                           1085
                           0185
                           1086
                           0186
                           1087
                           0187
                           1088
                           0188
                           1089
                           0189
                           1090
                           0190
                           1091
                           0191
                           1092
                           0192
                           1093
                           0193
                           1094
                           0194
                           1095
                           0195
                           1096
                           0196
                           1097
                           0197
                           1098
                           0198
                           1099
                           0199
                           1100
                           0200
                           1101
                           0201
                           1102
                           0202
                           1103
                           0203
                           1104
                           0204
                           1105
                           0205
                           1106
                           0206
                           1107
                           0207
                           1108
                           0208
                           1109
                           0209
                           1110
                           0210
                           1111
                           0211
                           1112
                           0212
                           1113
                           0213
                           1114
                           0214
                           1115
                           0215
                           1116
                           0216
                           1117
                           0217
                           1118
                           0218
                           1119
                           0219
                           1120
                           0220
                           1121
                           0221
                           1122
                           0222
                           1123
                           0223
                           1124
                           0224
                           1125
                           0225
                           1126
                           0226
                           1127
                           0227
                           1128
                           0228
                           1129
                           0229
                           1130
                           0230
                           1131
                           0231
                           1132
                           0232
                           1133
                           0233
                           1134
                           0234
                           1135
                           0235
                           1136
                           0236
                           1137
                           0237
                           1138
                           0238
                           1139
                           0239

```

```

805      VECT(I) = VECT(I-1) + 0.013125901          0262
C      DON-T GET EXCITED. THE CONSTANT IS JUST A FACTOR TO TRY TO    0263
C      DESTROY CYCLES IN THE STARTING VECTORS. THIS HELPS OUT THE    0264
C      ALGORITHM IN SOME CASES WITH MANY DEGENERACIES.               0265
C                                         266
DO 700   I=1,NROOT          0267
AROOT = ROOT(I)             0268
                                         269
C      TEST FOR REPEATED ROOT (WITHIN A LIMIT OF DELTA)           0270
GO TO (710,715) I           0271
715  IF((AROOT-ROOT(I-1))-DELTA) 720,71 ,710
710  IA = -1                0273
720  IA = IA + 1             0274
                                         275
ELIM1 = A(1) - ARROT        0276
ELIM2 = B(2)                 0277
JUMP = 1                     0278
                                         279
DO 750   J=1,NM1            0280
JUMP = JUMP+J+1              0281
                                         282
C      GET THE CORRECT PIVOT EQUATION FOR THIS STEP               0283
IF(ABSF(ELIM1)-ABSF(B(J+1)) 760,755,755
                                         285
C      FIRST (ELIM) EQUATION IS THE PIVOT THIS TIME             0286
755  IF(ELIM1) 757,756,757
756  ELIM1 = DELTA
757  B(J,2) = ELIM1
B(J,3) = ELIM2
B(J,4) = 0
TEMP = B(J+1)/ELIM1
                                         289
C      SAVE FACTOR FOR THE SECOND ITERATION. MARK IT AS CASE 1     0290
B(J,5) = TEMP.AND.KILLBIT          0291
                                         292
ELIM1 = A(JUMP)-AROOT - TEMP*ELIM2          0293
                                         294
                                         295
                                         0296

```

```

ELIM2 = B(J+2)
GO TO 750

C      SECOND EQUATION IS THE PIVOT THIS TIME.
760      B(J,2) = B(J+1)
          B(J,3) = A(JUMP) - ARROT
          B(J,4) = B(J+2)
          TEMP = ELIM1/B(J+1)

C      SAVE FACTOR FOR SECOND ITERATION. MARK IT AS CASE 2
          B(J,5) = TEMP•OR•13

ELIM1 = ELIM2 - TEMP*B(J,3)
ELIM2 = -TEMP*B(J+2)
750      CONTINUE

IF(ELIM1) 752,751,752
751      ELIM1 = DELTA
752      B(N,2) = ELIM1
          B(N,3) = B(N,4) = 0.
          B(N-1,4) = 0.

ITER = 1

IF(IA) 800,790,800

C      BACK SUBSTITUTE TO GET THIS VECTOR
790      L = N + 1
          DO 780 J=1,N
          L = L - 1
          VECT(L,I) = (VECT(L,I) - VECT(L+1,I)*B(L,3)) - VECT(L+2,I)*
          X      B(L,4))/B(L,2)
          GO TO (820,800) ITER

C      SECOND ITERATION. (BOTH ITERATIONS FOR REPEATED-ROOT VECTORS)
820      ITER = ITER + 1

```

```

890      ELIM1 = VECT(1,I)
          DO 830   J=1,NM1
          TEMP = B(J,5)*AND•1B
          IF (TEMP) 840,850
C
C CASE ONE.
850      VECT(J,I) = ELIM1
          ELIM1 = VECT(J+1,I) - ELIM1*B(J,5)
          GO TO 830
C
C CASE TWO.
840      VECT(J,I) = VECT(J+1,I)
          TEMP = B(J,5)*AND•KILLBIT
          ELIM1 = ELIM1 - VECT(J+1,I)*TEMP
C
830      CONTINUE
          VECT(N,I) = ELIM1
          GO TO 790
C
C ORTHOGONALIZE THIS REPEATED-ROOT VECTOR TO OTHERS WITH THIS ROOT
C IF THIS SECTION IS ENTERED WITH IA=0, THE SECTION IS A NO-OP.
800      DO 860   J1 =1,IA
          K = I - J1
          TEMP = 0.
C
          DO 870   J=1,N
          TEMP = TEMP + VECT(J,I)*VECT(J,K)
C
          DO 880   J=1,N
          VECT(J,I) = VECT(J,I) - TEMP*VECT(J,K)
          CONTINUE
C
          GO TO (890,900) ITER
C
          NORMALIZE THE VECTOR
900      TEMP = C.

```

```

910      DO 910   J=1,N
         TEMP = TEMP + VECT(J,I)**2
         TEMP = 1.0/SQRTF(TEMP)
               0368
               0369
               0370
               371
               0372
               0373
               0374
               0375
               0376
               0377
               0378
               0379
               0380
               381
               382
               383
               384
               385
               0386
               0387
               0388
               0389
               0390
               391
               0392
               0393
               0394
               0395
               396
               0397
               0398
               0399
               400
               0401
               0402
C       IF VECTOR ELEMENT IS VERY SMALL, SET IT TO ZERO.
C       IF(ABSF(VECT(J,I))-ETA) 919,920,92
919     VECT(J,I) = 0.0
920     CONTINUE
               0377
               0378
               0379
               0380
               381
               382
               383
               384
               385
               0386
               0387
               0388
               0389
               0390
               391
               0392
               0393
               0394
               0395
               396
               0397
               0398
               0399
               400
               0401
               0402
C       ROTATE CODIAGONAL VECTORS INTO VECTORS OF ORIGINAL ARRAY
C       - - - - -
               384
               385
               0386
               0387
               0388
               0389
               0390
               391
               0392
               0393
               0394
               0395
               396
               0397
               0398
               0399
               400
               0401
               0402
C       MOVE A TRANSFORMATION VECTOR OUT INTO BETTER INDEXING POSITION.
C       DO 955   J=IM,N
         B(J,2) = A(J1)
         J1 = J1 + J
               0392
               0393
               0394
               0395
               396
               0397
               0398
               0399
               400
               0401
               0402
C       MODIFY ALL REQUESTED VECTORS.
C       DO 960   K=1,NROOT
         TEMP = 0.
               0392
               0393
               0394
               0395
               396
               0397
               0398
               0399
               400
               0401
               0402
C       FORM SCALAR PRODUCT OF TRANSFORMATION VECTOR WITH EIGENVECTOR
DO 970   J=IM,N
               0392
               0393
               0394
               0395
               396
               0397
               0398
               0399
               400
               0401
               0402

```

```

970   TEMP = TEMP + B(J,2)*VECT(J,K)          0403
      TEMP = TEMP + TEMP                      0404
      DO 980 J=IM,N                           0405
      VECT(J,K) = VECT(J,K) - TEMP*B(J,2)       0406
      CONTINUE                                     0407
      JUMP = JUMP - IM                         0408
      IM = IM - 1                            0409
      410
      0411
      0412
      0413

C
      SUBROUTINE INPUT(N,NH,NO,IPT,ISTP,AL,TH,PH,BONDL,Z,ZS,BETA,U,COORD
     1, AW)
      DIMENSION IPT(5), ISTP(18), AL(18), TH(18), PH(18), BOND(18),
     1Z(18), ZS(18), BETA(40), U(40), COORD(3,18), SZ(9), SZS(9),
     2SBETA(9), SUS(2,9), SUP(2,9), SAW(9), NOAT(18),
     3AW(18), ROX(18,3,3), IST(18), CE(3,18)
C THIS ROUTINE READS IN DATA AND ARRANGES IT SUCH THAT CNDO MAKES USE OF IT.
C N IS THE NUMBER OF ATOMS READ IN. INITIALLY DUMMY ATOMS MAY BE READ IN
C WITH THEIR ATOMIC NUMBER = 0. THEY WILL BE LATER REMOVED IN A
C SUBROUTINE. N IS THUS INITIALLY SET EQUAL TO THE NUMBER OF ATOMS,
C NO IS THE NUMBER OF ORBITALS OCCUPIED.
C IPT IS AN ARRAY OF OPTIONS - SEE CNDO
C ISTP IS THE ARRAY OF STARTING POINTS USED IN CONSTRUCTING CARTESIAN
C COORDINATES FROM BOND ANGLES AND DISTANCES.
C AL IS THE ARRAY OF ANGLES ALPHA
C TH IS THE ARRAY OF ANGLES THETA
C PH IS THE ARRAY OF ANGLES PHI
C BONDL IS THE ARRAY OF BOND LENGTHS
C Z IS THE ARRAY OF CORE CHARGES
C ZS IS THE ARRAY OF SLATER EXPONENTS
C BETA IS THE ARRAY OF BETA ZEROS
C U IS THE ARRAY OF IONIZATION POTENTIALS
C COORD IS THE ARRAY OF CARTESIAN COORDINATES
C AW IS THE ARRAY OF ATOMIC WEIGHTS

```

```

C THE FOLLOWING ARRAYS ARE READ IN ONCE AND ARE USED TO CONSTRUCT THE
C ABOVE ARRAYS EACH TIME AN ATOM IS FED IN
C SZ IS ARRAY OF CORE CHARGES
C S2S IS THE ARRAY OF SLATER EXPONENTS
C SBETA IS ARRAY OF BETA ZEROS
C SUS US ARRAY OF IONIZATION POTENTIALS FOR S ORBITALS FOR CNDO/1
C FIRST ROW IS FOR CNDO/1, SECOND ROW FOR CNDO/2
C SUP IS IONIZATION POT. FOR P ORBITALS, FOLLOWING SUS CONVENTION
C SAW IS ARRAY OF ATOMIC WEIGHTS
C SUBROUTINE CONV CONVERTS BOND ANGLES AND DISTANCES INTO CARTESIAN COORD.
C
IF(IFBF=12345) 10,20,10
10 READ (50,100) (S2(I), I = 1,7)
      READ (50,100) (S2S(I), I = 1,9)
      READ (50,100) (SBETA(I), I = 1,9)
      READ (50,100) (SUS(I,I), I = 1,9)
      READ (50,100) (SUP(1,1), I = 1,9)
      READ (50,100) (SUP(1,1), I = 1,9)
      READ (50,100) (SUP(2,1), I = 1,9)
      READ (50,100) (SUP(2,1), I = 1,9)
      READ (50,100) (SAW(I), I = 1,9)
      WRITE (51,121)
      WRITE (51,101) (S2(I), I = 1,9)
      WRITE (51,122)
      WRITE (51,101) (S2S(I), I = 1,9)
      WRITE (51,123)
      WRITE (51,101) (SBETA(I), I = 1,9)
      WRITE (51,124)
      WRITE (51,101) (SUS(1,1), I = 1,9)
      WRITE (51,125)
      WRITE (51,101) (SUP(1,1), I = 1,9)
      WRITE (51,126)
      WRITE (51,101) (SUP(2,1), I = 1,9)
      WRITE (51,127)
      WRITE (51,101) (SUP(2,1), I = 1,9)
      WRITE (51,128)
      WRITE (51,101) (SAW(I), I = 1,9)
IFBF = 12345

```

```

20 CONTINUE
    READ (50,102)
    WRITE (51,102)
    READ (50,103), N, NH, NC, (IPT(I), I = 1,5)
    IF(N) 1000,1000,21
1000 STOP
21 CONTINUE
    DO 25 I = 1,N
25 READ (50,114) (ISTP(I), NOAT(I), AL(I), TH(I), PH(I), BONDL(I))
    WRITE (51,129)
    DO 26 I = 1,N
26 WRITE (51,126) (ISTP(I), NOAT(I), AL(I), TH(I), PH(I), BONDL(I),
CALL CONV(N,ISTP,AL,TH,PH,BONDL,NOAT,RCX,IST,CE,COORD)
    NOT = N-NH
    NT = 4*NOT+NH
    DO 30 I = 1,N
30 IN = NOAT(I)
    AW(I) = SAW(IN)
    Z(I) = SZ(IN)
    ZS(I) = S2S(IN)
    IW = IPT(4)
    DO 35 I = 1,NOT
35 IN = 4*I-3
    IN = NOAT(I)
    U(IM) = -SUS(IW,IN)
    BETA(IM) = -SBETA(IN)
    IM = IM+1
    IX = IM+2
    DO 36 J = IM,IX
36 DETA(J) = -SBETA(IN)
    B(J) = -SUP(IW,IN)
    NS1 = 4*NOT+1
    DO 40 I = NS1,NT
40 B(I) = -SUS(IW,1)
    BETA(I) = -SBETA(I)
    IF(IPT(I)+1) 45,50,45

```

```

45 WRITE (51,104) N,N,N,N,N, (IPT(I), I = 1,J)
  WRITE (51,105)
  WRITE (51,106)
  WRITE (51,101) (Z(I), I = 1,N)
  WRITE (51,108)
  WRITE (51,101) (ZS(I), I = 1,N)
  WRITE (51,109)
  WRITE (51,101) (DETA(I), I = 1,NT)
  WRITE (51,110)
  WRITE (51,101) (U(I), I = 1,NT)
  WRITE (51,112)
  WRITE (51,113) ((COORD(I,J), I = 1,J), J = 1,N)
50 DO 52 I = 1,NT
  BETA(I) = DETA(I)/27.21
52 U(I) = U(I)/27.21
      RETURN
100 FORMAT (9F5.3)
101 FORMAT (1H ,10F8.3)
102 FORMAT (8UH
1          )
103 FORMAT (8I2)
104 FORMAT (8UH
1          NO. ATOMS
1ITALS BRANCH CODE
105 FORMAT (8X,12,17X,12,18X,12,15X,5I2)
106 FORMAT (10H CHARACTS ON CORE)
108 FORMAT (17H SLATER EXPONENTS)
109 FORMAT (11H BETA ZEROS)
110 FORMAT (2H U)
112 FORMAT (12H COORDINATES)
113 FORMAT (1H ,2F12.0)
114 FORMAT (12,13,4F10.5)
121 FORMAT (22H TABLE OF CORE CHARGES)
122 FORMAT (26H TABLE OF SLATER EXPONENTS)
123 FORMAT (36H TABLE OF BETA ZEROS, NEGATIVE UNITS)
124 FORMAT (41H TABLE OF IONIZ. POT., S ORBITALS, CND0/1)
125 FORMAT (41H TABLE OF IONIZ. POT., P ORBITALS, CND0/1)

```

```

126 FORMAT (39H TABLE OF U•5*(I+A), S ORBITALS, CND0/2)
127 FORMAT (39H TABLE OF U•5*(I+A), P ORBITALS, CND0C/2)
128 FORMAT (23H TABLE OF ATOMIC MASSES)
129 FORMAT (67H STP AT.NO. ALPHA THETA PHI
130 FORMAT (1H ,13,3X,13,4F14•6)
END

C
C SUBROUTINE CONVN,ISTP,AL,TH,PH,BONDL,NOAT,ROX,IST,CE,CD)
C THIS SUBROUTINE CONVERTS ARRAYS OF BOND ANGLES AND DISTANCES INTO
C THE ARRAY CD, CARTESIAN COORDINATES.
C DUMMY ATOMS, IDENTIFIED BY NOAT = AT• NO• = ZERO ARE REMOVED FROM THE
C FINAL ARRAY. HYDROGEN ATOMS, IDENTIFIED BY NOAT = 1 ARE PLACED AT
C END OF ARRAY.
C N IS THE NUMBER OF POSITIONS TO BE TRACED OVER
C ISTP IS THE STARTING POINT BEFORE EACH TRACE
C AL, TH, AND PH, CONTAIN THE ANGLES FOR ROTATIONS ABOUT Z, X, THEN Y AXIS
C
C BONDL CONTAINS THE BOND LENGTHS
C AW CONTAINS THE ATOMIC MASSES
C ROX, CE, AND IST ARE WORKING SPACES
C CD IS THE MATRIX OF COORDINATES DETERMINED BY THE PROGRAM
C DIMENSION ISTP(18), AL(18), TH(18), PH(18), BONDL(18), NOAT(18),
1 ROX(18,3,3), IST(18), CD(3,18), CE(3,18)
DO 217 I = 1,N
CA = COSF(0.017453293*AL(I))
SA = SINF(0.017453293*AL(I))
CT = COSF(0.017453293*TH(I))
ST = SINF(0.017453293*TH(I))
CP = COSF(0.017453293*PH(I))
SP = SINF(0.017453293*PH(I))
ROX(I,1,1) = CA*CP+SA*ST*SP
ROX(I,1,2) = -SA*CP+CA*ST*SP
ROX(I,1,3) = CT*SP
ROX(I,2,1) = SA*CT
ROX(I,2,2) = CA*CT

```

```

ROX(1,2,2) = -ST
ROX(1,3,1) = -CA*SP+SA*ST*CP
ROX(1,3,2) = SA*SP+CA*ST*CP
217 ROX(1,3,3) = CT*CP
IA = 0
IB = 0
230 IF(IA-N) 235,4,4
235 IA = IA+1
IA1 = IA-1
IF(IA1) 280,280,240
240 IF(ISTP(IA)-IB) 245,245,270
C BEGIN RETRACE TO PREVIOUS STARTING POINT
C
C 245 ISTX = IST(IB)
DO 260 I = 1,IA1
260 CD(1,I) = CD(1,I)+BONDL(ISTX)
DO 262 I = 1,3
DO 262 J = 1,IA1
CE(I,J) = 0.0
DO 262 K = 1,3
262 CE(I,J) = CE(I,J)+ROX(ISTX,K,I)*CD(K,J)
DO 263 I = 1,3
DO 263 J = 1,IA1
263 CD(I,J) = CE(I,J)
IB = IB-1
IF(ISTP(IA)-IB) 245,245,270
C ADDITION IF IA-TH ATOM
C
C 270 DO 272 I = 1,3
DO 272 J = 1,IA1
CE(I,J) = 0.0
DO 272 K = 1,3
272 CE(I,J) = CE(I,J)+ROX(IA,I,K)*CD(K,J)
DO 273 I = 1,3

```

```

273 DO 473 J = 1,IAJ
273 CD(I,J) = CE(I,J)
DO 275 I = 1,IA1
275 CD(1,I) = CD(1,1)-BOND(LIA)
280 DO 285 I = 1,3
285 CD(I,IA) = 0.0
IB = IB+1
1ST(1B) = IA
GO TO 230

```

C REARRANGE ATOMS

```

4 NO = N
DO 30 I = 1,N
IF(NOAT(I)) 30,10,30
10 DO 20 J = 1,N
J1 = J+1
NOAT(J) = NOAT(J1)
DO 20 K = 1,3
20 CD(K,J) = CD(K,J1)
NOAT(N) = 1
NO = NO-1
I=I 1
30 CONTINUE
N = NO

```

C C

```

C ARRANGE HYDROGEN ATOMS LAST
C
DO 50 I = 1,N
IF(NOAT(I)-2) 40,40,50
40 I1 = I+1
DO 42 J = I1,N
IF(NOAT(J)-2) 42,42,43
42 CONTINUE
GO TO 60
43 DO 44 K = 1,3

```

```

44 CE(K,1) = CD(K,J)
ISN = NOAT(J)
JS = J+1
NO = J-1
DO 45 K = 1,NO
JS = JS-1
JS1 = JS-1
NOAT(J) = NUAT(J,1)
DO 45 L = 1,J
45 CD(L,JS) = CD(L,JS1)
DO 46 L = 1,J
46 CD(L,I) = CE(L,1)
NOAT(I) = ISN
50 CONTINUE
60 RETURN
END
END
FINIS
-EXECUTE.
1   1   2   3   4   5   6   7
12  65  975 12  1625 195 2275 26
9   9   13  17  21  25  31  39
1306 539 932 1405 1944 2558 3238 4020
      354 596 830 1067 1319 1585 1866
7176 3166 5946 959414051133162539032272
      1258 2565 4001 5572 7275 911111010
1   7   9   11  12  14  16  19
1   ETHANE STAGGER
10  6   7   0   215
1   6
2   1   120.0 110.86 1.102
2   1   110.86 1.102
2   1   120.0 110.86 1.102
2   6   60.0 60.0 -69.14 1.102
3   1   60.0 60.0 -69.14 1.102
3   1   180.0 180.0 -69.14 1.102

```

3	1		60.0	-69.14	1.102
2					•775
3				-90.●	
1	10	6 7 1	25 _U	ETHANE (ECLIPSED)	
1	6				
2	1		120.0	111.28	1.102
2	1		120.0	111.28	1.102
2	1			111.28	1.102
2	6				1.4633
3	1		60.00	-68.72	1.102
3	1		180.0	-68.72	1.102
3	1		60.00	-68.72	1.102
2	3				•775
				-90.●	

1419

APPENDIX

II Computer output of Water (H_2O)
(Sample calculation)

H2O OPTIMIZE							
STP	AT. NO.	ALPHA	THETA	PHI	BOND LENGTH		
1	8	-0	-0	-0	-0	-0	-0
2	1	52.110000	-0	-0	-0	1.028900	
2	1	-52.110000	-0	-0	-0	1.028900	
2	-0	-0	-0	-0	-0	-0	-0
NO. ATOMS	NO. ATOMS	NO. ATOMS	NO. OCCUPIED ORBITALS	4	4	4	4
3	2	2	2	2	2	2	2
CHARGES ON CORE							
6.000	1.000	1.000					
SLATER EXPONENTS							
2.275	1.200	1.200					
BETA ZEROS							
-31.000	-31.000	-31.000	-31.000	-31.000	-31.000	-31.000	-31.000
U	-25.390	-9.111	-9.111	-9.111	-9.111	-7.176	-7.176
COORDINATES							
0	0	0	0	0	0	0	0
.63189631	-.81199893	0	0	0	0	0	0
.63189631	.81199893	0	0	0	0	0	0
COORDINATES IN ATOMIC UNITS							
0	0	0	0	0	0	0	0
1.194134	-1.534485	0	0	0	0	0	0
1.194134	1.534485	0	0	0	0	0	0
DIRECTION COSINES							
0	0	0	0	0	0	0	0
-0.614147	0	0	0	0	0	0	0
-0.614147	0	0	0	0	0	0	0
0	0	0	0	0	0	0	0
0	0	0	0	0	0	0	0
0	0	0	0	0	0	0	0
0	0	0	0	0	0	0	0
0	0	0	0	0	0	0	0
DISTANCES IN ATOMIC UNITS							
0	1.944377	1.944377	1.944377	1.944377	1.944377	1.944377	1.944377
1.944377	0	0	0	0	0	0	0
1.944377	3.068970	3.068970	3.068970	3.068970	3.068970	3.068970	3.068970

RHO	0	3.378355	3.378355	
	3.378355	0	3.682764	
	3.378355	3.682764	0	
TAU	0	.309353	.309353	
	-.309353	0	0	
	-.309353	0	0	
OVERLAP				
	1.000000	0	0	434263
	0	1.000000	0	434263
	0	0	0	.220063
	0	1.000000	0	.220063
	0	0	0	.282785
	0	220063	-.282785	.282785
	0	220063	-.282785	0
	0	220063	-.282785	0
GAMMA				
	.826465	.476151	.476151	
	.476151	.750000	.320779	
	.476151	.320779	.750000	
V	0	.476151	.476151	
	2.856904	0	.320779	
	2.856904	.320779	0	
F				
	-.933113	0	0	-319194
		-.334840	0	-.319194
	0	0	-.334840	-.161751
	0	0	0	.207853
	0	0	-.334840	-.207853
	0	0	0	0
	-.319194	-.161751	.207853	-.263727
	-.319194	-.161751	-.207853	-.076572
			0	-.263727
			0	-.076572

ORBITAL ENERGIES

-1.442662 - .759905 - .701810 - .654866 .289195 .309628

C

	.880226	.051057	-0	.000000	.333614	.333614
	.000000	-.000000	.753527	.000000	-.464864	.464864
	-.295445	.836979	.000000	-.000000	.325713	.325713
	.000000	-.000000	.000000	-1.000000	-.000000	-.000000
	-.371370	-.544648	-.000000	.000000	.531613	.531613
	.000000	.000000	-.657417	.000000	-.532824	.532824

P

	1.724169	-.404680	.000000	.000000	.394850	.394850
	-.404680	1.406282	.000000	-0	.579297	.579297
	.000000	.000000	1.135605	-.000000	-.700575	.700575
	.000000	-0	-.000000	2.000000	.000000	-0
	.394850	.579297	-.700575	.000000	.866972	.002577
	.394850	.579297	.700575	-0	.002577	.866972

PA

6.266056 .866972 .866972

F

	-1.139160	.167227	-0	-0	-.413198	-.413198
	.167227	-.409526	-0	0	-.299668	-.299668
	-0	-0	.297673	.000000	.374643	.374643
	-0	0	.000000	-.654869	-.000000	0
	-.413198	-.299668	.374643	-.000000	-.229602	.076986
	-.413198	-.299668	-.374643	0	-.076986	-.229602

ENERGY

-17.570850 -.752501 -.752501

-.412826 .010344

-.412826

10 ITERATIONS

-19.89115807

INITIAL DISTRIBUTION LIST

	No. Copies
1. Defense Documentation Center Cameron Station Alexandria, Virginia 22314	20
2. Library Naval Postgraduate School Monterey, California 93940	2
3. Library R.O.K. Naval Academy, Chinhae, Republic of Korea	2
4. Department of Material Science and Chemistry Naval Postgraduate School Monterey, California 93940	3
5. Prof. William M. Tolles Department of Chemistry Naval Postgraduate School Monterey, California 93940	3
6. Prof. John H. Duffin Department of Chemistry Naval Postgraduate School Monterey, California 93940	1
7. Imagawa Tetsuo 2075 Rainier Court Seaside, California	1
8. LT. C.D. Kimble Department of Chemistry Naval Postgraduate School	1
9. LT C.S. Yun Department of Chemistry R.O.K. Naval Academy Chinhae, Republic of Korea	7

UNCLASSIFIED

Security Classification

DOCUMENT CONTROL DATA - R&D

(Security classification of title, body of abstract and indexing annotation must be entered when the overall report is classified)

1. ORIGINATING ACTIVITY (Corporate author)		2a. REPORT SECURITY CLASSIFICATION UNCLASSIFIED
Naval Postgraduate School Monterey, California		2b. GROUP
3. REPORT TITLE APPROXIMATE SELF-CONSISTENT FIELD CALCULATIONS OF MOLECULAR POTENTIAL SURFACES		
4. DESCRIPTIVE NOTES (Type of report and inclusive dates) Thesis, M. S., June 1967		
5. AUTHOR(S) (Last name, first name, initial) YUN, Chang Sop		
6. REPORT DATE June 1967	7a. TOTAL NO. OF PAGES	7b. NO. OF REFS 49
8a. CONTRACT OR GRANT NO.	9a. ORIGINATOR'S REPORT NUMBER(S)	
b. PROJECT NO.		
c.		
d.	9b. OTHER REPORT NO(S) (Any other numbers that may be assigned this report)	
10. AVAILABILITY/LIMITATION NOTICES This document is subject to special export controls and each transmittal to foreign nationals may be made only with prior approval of the Naval Postgraduate School.		
11. SUPPLEMENTARY NOTES	12. SPONSORING MILITARY ACTIVITY	


13. ABSTRACT

The approximate Self-Consistent Field Molecular Orbital Theory (ASCFT) with complete neglect of differential overlap (CDO) has been applied to the calculation of electronic structure for several selected molecules in this text. The theory leads to calculated equilibrium geometry configurations and the barrier to internal rotation of ethane, inversion barrier of ammonia and the barrier for cis to trans conversion for difluorodiazine. These results are in reasonable agreement with experimental values in most cases. The stretching force constants are higher than experimental values by a factor of approximately two. The orbital energy levels for ammonia and for oxygen difluoride as a function of bond angles were in reasonable agreement with the full LCAO-SCF Calculations. A variation of parameters to find a new set of parameters was attempted with unsuccessful results.

The extended Hückel Theory (EH) can be applied to aliphatic hydrocarbons but its application to non-hydrocarbon molecules is quite limited.

UNCLASSIFIED

Security Classification

14 KEY WORDS	LINK A		LINK B		LINK C	
	ROLE	WT	ROLE	WT	ROLE	WT
<p>Approximate Self-Consistent field theory Extended Huckel Molecular Orbital Theory Complete Neglect of Differential Overlap Barrier -- NH_3 (inversion) C_2H_6 (eclipsed to stagger form) N_2F_2 (cis to trans) LCAO-SCF (Linear Combination of Atomic Orbital Self-Consistent Field) force constant equilibrium geometry (Bond length and Bond angle) ground singlet and doublet states Energy level diagram for F_2O NH_3 J.A. Pople R. Hoffmann</p> 						







thesY86

Approximate call no.

DUDLEY KNOX LIBRARY



3 2768 00415857 6

DUDLEY KNOX LIBRARY